

# MULTIFUNCTIONAL DIGITAL COLOR SYSTEMS / MULTIFUNCTIONAL DIGITAL SYSTEMS **e-Filing Guide**

## ES9455 MFP ES9465 MFP/ES9475 MFP

©2013 Oki Data Corporation All rights reserved Under the copyright laws, this manual cannot be reproduced in any form without prior written permission of Oki Data.


## **Preface**

Thank you for purchasing OKI Multifunctional Digital Systems. This manual explains how to use the e-Filing. Read this manual before using your Multifunctional Digital Systems. Keep this manual within easy reach, and use it to configure an environment that makes best use of the OKI MFP's functions.

## How to read this manual

## Symbols in this manual

In this manual, some important items are descried with the symbols shown below. Be sure to read these items before using this equipment.



Indicates a potentially hazardous situation which, if not avoided, could result in death, serious injury, or serious damage, or fire in the equipment or surrounding objects.

Note

Indicates information to which you should pay attention when operating the equipment.

Other than the above, this manual also describes information that may be useful for the operation of this equipment with the following signs:

injury, partial damage to the equipment or surrounding objects, or loss of data.



Describes handy information that is useful to know when operating the equipment.



Pages describing items related to what you are currently doing. See these pages as required.

## Model and series names in this manual

In this manual, each model name is replaced with the series name as shown below.

Model name Series name in this manual	
ES9455 MFP	ES9455 MFP*1
ES9465 MFP/ES9475 MFP	ES9475 MFP Series

\*1 The e-Filing functions can be used only when a hard disk is installed.

## Screens and Operation Procedures

- In this manual, the screens and the operation procedures in Windows are described for Windows 7. The details on the screens may differ depending on how the equipment is used, such as the status of the installed options, the OS version and the applications.
- If you use Windows Server 2008 R2, refer to the operation procedure for Windows 7, though the screens or the menu names. etc. may differ.
- The illustration screens used in this manual are for paper in the A/B format. If you use paper in the LT format, the display or the order of buttons in the illustrations may differ from that of your equipment.

## Trademarks

- The official name of Windows XP is Microsoft Windows XP Operating System.
- The official name of Windows Vista is Microsoft Windows Vista Operating System.
- The official name of Windows 7 is Microsoft Windows 7 Operating System.
- The official name of Windows 8 is Microsoft Windows 8 Operating System.
- The official name of Windows Server 2003 is Microsoft Windows Server 2003 Operating System.
- The official name of Windows Server 2008 is Microsoft Windows Server 2008 Operating System.
- The official name of Windows Server 2012 is Microsoft Windows Server 2012 Operating System.
- Microsoft, Windows, Windows NT, and the brand names and product names of other Microsoft products are trademarks of Microsoft Corporation in the US and other countries.
- Apple, AppleTalk, Macintosh, Mac, Mac OS, Safari, and TrueType are trademarks of Apple Inc. in the US and other countries.
- Adobe, Acrobat, Reader, and PostScript are either registered trademarks or trademarks of Adobe Systems Incorporated in the United States and/or other countries.
- Mozilla, Firefox and Firefox logo are trademarks or registered trademarks of Mozilla Foundation in the U.S. and other countries.
- IBM, AT and AIX are trademarks of International Business Machines Corporation.
- NOVELL, NetWare, and NDS are trademarks of Novell, Inc.
- Other company and product names given in this manual or displayed in this software may be the trademarks of their respective companies.

## Chapter 1 e-Filing OVERVIEW

e-Filing Features	6
e-Filing Functions	. 8
Functions operated with this equipment	. 8
Functions operated with a client computer	9

## Chapter 2 OPERATIONS WITH THIS EQUIPMENT

Printing Documents	12
Printing an entire document	12
Test print	
Storing Documents	
Copying and storing to e-Filing	17
Scanning to e-Filing	
Deleting Documents	25
Managing User Boxes/Folders	27
Creating user boxes	
Editing user boxes	29
Deleting user boxes/folders	

## Chapter 3 OVERVIEW OF e-Filing WEB UTILITY

Before Using the e-Filing Web Utility	
Getting Started With the e-Filing Web Utility	
Logging in as a user	
Logging in as a system administrator	
About the Main Tabs	
[Documents] tab	
[Preferences] tab	
[Administration] tab	
Log-in link	

## Chapter 4 HOW TO MANAGE USER BOXES/FOLDERS

Managing User Boxes and Folders	44
Creating user boxes and folders	
Deleting user boxes and folders	
Renaming user boxes and folders	
Modifying and displaying user box and folder properties	

## Chapter 5 MANAGING DOCUMENTS

How To Manage Documents	60
Displaying documents	60
Renaming documents	
Deleting documents	
Printing documents	

Storing documents	70
Archiving documents	73
Sending Email	78

## Chapter 6 EDITING DOCUMENTS

About the Document Control Buttons	88
Editing With Pages in Your Documents	
Displaying document and page properties	
Copying pages from one document to another	
Copying pages from a document to a box or folder	
Deleting pages from a document	
Inserting a blank page into a document	101
Moving pages within a document	104
Moving and Merging Documents	107
Moving documents	107
Merging documents	

## Chapter 7 SYSTEM ADMINISTRATION

Safeguarding Data	114
Erasing boxes	114
Unlocking user boxes	
INDEX	117

# e-Filing OVERVIEW

This chapter describes overview of the e-Filing features and functions.

e-Filing Features	6
e-Filing Functions	8
Functions operated with this equipment	
Functions operated with a client computer	9

1


## e-Filing Features

The e-Filing is installed in a hard disk of this equipment. It allows you to store documents and to print/edit/manage the stored documents.

This section describes the system of e-Filing for storing documents.

#### Note

This function is available only when a hard disk is installed in the equipment.



#### **Public Box**

The public box is an e-Filing created by default. All users can access it, so it is suitable to store shared documents which any user may need to work with. Since the public box is a built-in system box, you cannot change the name of the box / create a new box / delete the box.

#### **User Box**

The user box is an e-Filing that each user can create. The user box can be protected by a password to limit access. It is suitable for specific users or an administrator to store confidential documents. You can also create a user box without setting a password. In this case, all users can access the user box as well as the public box. (Up to 200 user boxes can be created.)

#### Folders

You can create folders in each box. However, you can create only one level of folders within each box. You cannot create subfolders within folders.

(Up to 100 folders can be created in a box.)

#### **Documents**

Documents can be stored in a box or folder in the following methods.

(Up to 400 documents can be stored in a box or folder. / Up to 200 pages can be contained in a document.)

- · Copying documents and storing to e-Filing
- · Scanning documents and storing to e-Filing
- · Printing documents in a client computer and storing to e-Filing
- Received Internet Faxes / received faxes are forwarded to store to e-Filing using forward functions.
- Received Internet Faxes / received faxes are forwarded to store to e-Filing using forward mailbox functions.

#### Notes

- Storing the received faxes is available only when FAX Unit (optional) is installed.
- Depending on the amount of data stored in e-Filing, it may take some time from when the equipment is turned on to e-Filing becoming ready for use.

Tips

- For details of the forward functions, refer to the TopAccess Guide.
- For details of the forward mailbox functions, refer to the GD-1250/GD-1260 Operator's Manual for FAX Unit and TopAccess Guide.

## e-Filing Functions

## Functions operated with this equipment

Below is a list of e-Filing functions that you can operate with this equipment. For details of the operation, see the references described below.

## **Printing documents**

The following functions allow you to print documents stored in the e-Filing.

- To print an entire document
   P.12 "Printing an entire document"
- To print specified pages of the document for confirmation
   P.15 "Test print"

## □ Storing documents

The following functions allow you to store documents in the e-Filing.

- To copy and store documents
- P.17 "Copying and storing to e-Filing"
- To scan and store documents
   P.22 "Scanning to e-Filing"

## Deleting documents

To delete documents in the e-Filing P.25 "Deleting Documents"

## □ Managing user boxes/folders

The following functions allow you to manage user boxes and folders in the e-Filing. You cannot create and edit folders in boxes using the control panel. Folders can be created using a client computer.

- To create new user boxes
   P.27 "Creating user boxes"
- To change the registered user box name and password
   P.29 "Editing user boxes"
- To delete user boxes and folders
   P.31 "Deleting user boxes/folders"

## Functions operated with a client computer

Below is a list of e-Filing functions that you can operate with a client computer (e-Filing web utility). For details of the operation, see the references described below.

#### Note

e-Filing web utility supports only Windows. Mac OS and other computers are not supported.

## □ Managing user boxes/folders

The following functions allow you to manage user boxes and folders in the e-Filing.

- · To create new user boxes and folders
  - P.44 "Creating user boxes and folders"
- To delete user boxes and folders
   P.47 "Deleting user boxes and folders"
- To edit (renaming and changing Properties) user boxes and folders
   P.50 "Renaming user boxes and folders"
  - P.54 "Modifying and displaying user box and folder properties"

## □ Managing documents

The following functions allow you to manage documents stored in the e-Filing.

- To display document image files in thumbnail view and list view
- P.60 "Displaying documents"
  To rename documents
- P.61 "Renaming documents"
- To delete documents
  - P.63 "Deleting documents"
- To print documents (entire document/test print)
- P.64 "Printing an entire document"
   P.67 "Selecting test print"
- To store documents by printing operation
   P.70 "Storing documents"
- To archive documents
   P.73 "Archiving documents"
- To send documents as Emails
- 📖 P.78 "Sending Email"

## Editing documents

The following functions allow you to edit documents stored in the e-Filing.

- To display document and page Properties
   P.89 "Displaying document and page properties"
- To copy/cut pages from a document and paste them into another one
   P.90 "Copying pages from one document to another"
- To copy/cut pages from a document and save them as a new document
- P.95 "Copying pages from a document to a box or folder"
- To delete pages from a document
- P.99 "Deleting pages from a document"
- To insert blank pages into a document
   D 101 "Inserting a blank page into a site
- P.101 "Inserting a blank page into a document"
- To move pages within a document to arrange the page order
   P.104 "Moving pages within a document"
- To move documents between boxes or folders
   P.107 "Moving documents"
- To copy an entire document and insert them into another document
  - P.109 "Merging documents"

Tips

- You can import e-Filing documents into a client computer using TWAIN Driver and File Downloader.
- You can back up or restore documents in e-Filing and various settings of e-Filing using the e-Filing Backup/Restore Utility.

# 2

# **OPERATIONS WITH THIS EQUIPMENT**

This chapter describes e-Filing functions that you can operate using the control panel of this equipment.

Printing Documents	12
Printing an entire document	
Test print	
Storing Documents	
Copying and storing to e-Filing	
Scanning to e-Filing	22
Deleting Documents	25
Managing User Boxes/Folders	27
Creating user boxes	
Editing user boxes	
Deleting user boxes/folders	31

## **Printing Documents**

You can print documents stored in the e-Filing using the control panel of this equipment. P.12 "Printing an entire document" P.15 "Test print"

## Printing an entire document

You can print an entire document.

Press the [Filing Box] button on the control panel.

	PQRS TUV WXYZ 7 8 9
FILING BOX	* 0 #
Fax (1)	AUTHENTICATION C
DATA IN MEMORY	PRINT DATA ATTENTION

**?** Select the box that contains a document you want to print.

훩 e-FILIN	G			☆ TEMPLATE 🔎	?
BOX NUMBER:		1			
PUBLIC BOX	001 UserBox01	002	003 T UserBox03	004 DiserBox04	<b>^</b>
005	006 UserBox06	007	008 DiserBox08	009 UserBox09	21
					_
PRINT		BOX SETTING		2011/05/10 JOB STA 06: 33 JOB STA	TUS

Press 🔿 or 🔽 to switch the pages. You can also specify the box number (3-digit) using the digital keys.

#### Password entry

When the password has been set to the selected user box, the password entry screen is displayed. In this case, press [PASSWORD], enter the password using the digital keys or the on-screen keyboard, and then press [OK].

Select BOX.			- TEMPLA	TE 2 ?
Enter BOX Password.				
	BOX NUMBER	: 001		
	BOX NAME	: UserBox01		
	PASSWORD	*****		
	$(\mathbf{j})$			
		CA		× I
r.			06:34	2 <sup>2</sup>

#### Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access.
  - When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- · The password input is displayed in the blank symbols.

**3** If the document is stored in a folder, select the folder and press [OPEN].



If the document is stored outside of the folder, this operation is not necessary.

**4** Select the document. To change the print settings, press [SETTINGS]. To perform printing without changing them, press [PRINT].

휅 e-FILING		👷 TEMPL	ATE	?
► 001 UserBox01 ► Folder01				
Document Name	Date,Time	Paper	Pages	
DOC110508	10, 06:04	A4	1	~
DOC110510	10, 06:05	A4	3	1
				1
8			ſ	
				$\mathbf{\mathbf{v}}$
		OPEN	I PRI	NT
PRINT BC 2 TING				
		2011/05/10 06:38	JOB STAT	US 🕨


If you press [SETTINGS], proceed to step 5. If you press [PRINT], printing will start. When you want to stop printing, see "Deleting print job" in step 6.

Tip

Press Press Press to preview thumbnail images of the documents. Select the desired one and press [OPEN] to display its contents. Press to return to the list.

휳 e-FILING	i	TEMPLATE
▶ 001 UserBox01	► Folder01	
	Document Name	- Cm
ご定 〕1歳 DOC110508	DOC110510	
▲ RETURN	DELETE SETTINGS TEST PF	
PRINT	BOX SETTING	
		2011/05/10 JOB STATUS

## **5** Change the print settings as necessary.



You can operate the print settings as below. For step 3 to 8, when each button of the menu is pressed, the setting screen appears. Perform the appropriate operations. These operations of settings are the same as the one of copy modes. For details of the operation, refer to the **Copying Guide**.

- 1) Select the paper feeder. However, if the selected paper size is different from the actual one, the selection will be cancelled and automatic paper selection will be applied.
- 2) Key in the number of copies to be printed using the digital keys.
- Select the duplex printing mode. If you do not want to print on both sides of the paper, select [1 SIDE] in the menu.
- 4) Select the finishing mode. The available finishing modes differ depending on the type of finishing device installed.
- 5) Select the receiving tray. This button is available only when the Finisher (optional) is installed.
- 6) Set the position and width of the margin.
- 7) Set the position of the date and time to be printed.
- 8) Set the position of the page number to be printed.

## 6 Press [PRINT].



#### · Deleting print jobs

Follow the procedure below to stop the printing of the document (delete print jobs).


- 1) Press [JOB STATUS].
- 2) On the job status menu, display the print job list or the scan job list.
- 3) Select the job you want to delete, and then press [DELETE].
- 4) The delete confirmation screen appears. Press [DELETE].

For details of deleting print jobs, refer to the Copying Guide.

## Test print

You can print specified pages of the document for confirmation.

**1** Press the [Filing Box] button on the control panel.



**2** Select the box or folder that contains documents you want to print.

e-FILINO	G			☆ TEMPLATE	?
BOX NUMBER:					10
PUBLIC BOX	001 UserBox01 UserBox06	002 UserBox02	003 UserBox03	004 UserBox04	1 21
PRINT		BOX SETTING		2011/05/10 06:33 JOB	STATUS

The instructions of the operating procedure as to selecting a box/folder are omitted, because they are the same as those for one of printing an entire document.


P.12 "Printing an entire document"

## 3 Select the document you want to print, and then press [TEST PRINT].

📦 e-FILING		👷 TEMPL	ATE ,	?
► 001 UserBox01				
Document / Folder Name	Date,Time	Paper	Pages	
Folder01	11, 02:25			
DOC110509	10, 04:32	A4	1	4
DOC110510	10, 06:45	A4	3	-
				~
		OPEN	P	RINT
PRINT BOX SETTING	(2)			
	Y	2011/05/10 06:46	JOB ST A	TUS 🗼

Tip

Press Press preview thumbnail images of the documents. Select the desired one and press [OPEN] to display its contents. Press to return to the list. **4** Key in page numbers in [FIRST PAGE] and [LAST PAGE], then press [PRINT].



- Select [FIRST PAGE] or [LAST PAGE], then specify the page numbers using the digital keys on the control panel.
- If you press the [CLEAR] button on the control panel, the value entered in the currently selected box can be deleted.
- To print entire pages of the document, press [ALL PAGES].

#### • Deleting print jobs

Follow the procedure below to stop the printing of the document (delete print jobs).

- 1) Press [JOB STATUS].
- 2) On the job status menu, display the print job list or scan job list.
- 3) Select the job you want to delete, and then press [DELETE].
- 4) The delete confirmation screen appears. Press [DELETE].
- For details of deleting print jobs, refer to the Copying Guide.

## **Storing Documents**

You can store documents in e-Filing using the control panel of this equipment.

- P.17 "Copying and storing to e-Filing"
- P.22 "Scanning to e-Filing"

#### Notes

- · Store confidential documents in a user box protected by a password.
- Up to 400 documents can be stored in a box or folder, and up to 200 pages can be contained in a document. However, the total storage capacity of e-Filing and the shared folder is approx. 230 GB. Documents can only be stored within the storage capacity limit. The available space can be checked with the [Device] tab in TopAccess.
- Saving in the e-Filing is not for permanent use. Delete unnecessary documents immediately.
   P.25 "Deleting Documents"

#### Tips

- When you store documents in user boxes and folders, you need to create them in advance.
   P.27 "Creating user boxes" (Operating with this equipment)
  - P.44 "Creating user boxes and folders" (Operating with a client computer)
- You can set the storage period for documents in the Box Properties window in a user box. The documents will be deleted after the specific number of days have passed.
   D 5.4 "Medifying and displaying user box and folder properties" (Operating with a client computer).

P.54 "Modifying and displaying user box and folder properties" (Operating with a client computer)

## Copying and storing to e-Filing

You can copy and store documents in e-Filing. The e-Filing documents can be copied and stored at the same time.

#### Notes

- · Documents, whose paper sizes are shown below, cannot be stored in e-Filing.
  - Custom paper
  - Non-standard size paper (MPT)
- A document stored by "Copying and storing to e-Filing" is suitable for output, but not for importing as an image into a client computer. To get the best image quality for importing an image into your computer, store the document by "Scanning to e-Filing".

P.22 "Scanning to e-Filing"

### Place the original(s) and set the copy mode as necessary.

For details of placing original(s) and copy mode settings, refer to the Copying Guide.

### Note


On copy mode settings, even when "TWIN COLOR COPY" or "MONO COLOR" is selected on the [IMAGE] tab, this mode is invalid for storing documents in e-Filing. This mode is also invalid for copying documents at the same time as storing them.

## **9** Press [STORAGE] on the copying screen.

💼 COPY 🛛	STORAGE SE	ettings , 👷 tei	MPLATE
READY	- (b)		<sup>Set</sup> 1
A4	ORG → COPY	NON-SORT NON-STAPLE	FULL COLOR BLACK BLACK AUTO COLOR
A3 I A4-R I B4 I	1→1 SMPLEX 2-SDED	TEXT /PHOTO	
BASIC	EDIT	IMAGE	PROOF COPY
U. LOID	2011	2011/05/1	

If the copying screen is not displayed, press the [COPY] button on the control panel.

## **3** Press [STORE TO E-FILING].



## 4 Press [BOX/FOLDER].

in COPY	STORAGE	SETTINGS	🕨 🙀 TEM	PLATE
READY				SET 1
STORE TO E-FLING	COPY & FILE			
BOX / FOLDER	BOX No.			
- Cm	BOX NAME			
9	FOLDER NAME			
	OC110510			
	R	ESET	CANCEL	ОК
			2011/05/10 06:49	JOB STATUS

**5** Select the box in which you want to store the data.

🔋 e-FILINC	à			☆ TEMPLATE 🗼 ?
BOX NUMBER:				
PUBLIC BOX	001	002	003 T	004 UserBox04 1
005 UserBox 05	006 UserBox06	007	008 IIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIII	009 21 UserBox09
			C	ANCEL
				2011/05/10 JOB STATUS

Press 🔿 or 🔽 to switch the pages. You can also specify the box number (3-digit) the using digital keys.

#### · Password entry

When the password has been set to the selected user box, the password entry screen is displayed. In this case, press [PASSWORD], enter the password using the digital keys or the on-screen keyboard, and then press [OK].

Select BOX.		CENPLATE
Enter BOX Password		
	BOX NUMBER	: 001
	BOX NAME	: UserBox01
	PASSWORD	
	V	
- F		06:52 JUL 2 US

## Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access.
- When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- The password input is displayed in the blank symbols.

## **6** To store the original(s) in the selected box, press [OK].

1	COPY	STORAGE	SETTINGS	🕨 🙀 TEMPL	ATE 🕨	?
RE	EADY					<sup>Set</sup> 1
▶ 001	UserBox01					
	Document / Folder N	lame	Date,Time	Paper	Pages	
	Folder01		11, 02:25			
	DOC110509		10, 04:32	A4	1	
						$\mathbf{\mathbf{x}}$
			OPEN	CANCEL		m
				2011/05/10 07:06	JOB ST	ATUS ,

#### Storing in a folder

Select the folder and press [OPEN], the list in the folder is displayed. To store the original(s) in the selected folder, press [OK].

💼 COPY	STORAGE	SETTINGS	🕨 🔂 TEMPL	ATE 🕨	?
READY				5	зет <b>1</b>
► 001 UserBox01					
Document / Folder	lame	Date,Time	Paper	Pages	
Folder 01		11, 02:25			
DOC11050		10, 04:32	A4	1	1
U U					1
					·
		OPEN	CANCEL	0	<
		~~	2011/05/10 07:07	JOB STA	TUS 🗼

7 Change the document name as necessary, then press [OK].



#### Renaming the documents

When you press [DOCUMENT NAME], the on-screen keyboard is displayed. Key in the document name using the keyboard and the digital keys (up to 64 characters), then press [OK].

DOC110510_
$\leftarrow \rightarrow$
Basic   Back Space  Clear
1234567890-+ QWERTYUIOP[]\
A S D F G H J K L : '
Z X C V B N M , / @

For details of the on-screen keyboard, refer to the Quick Start Guide.


#### Tips

- A character string composed of "DOC", year, month and date is displayed by default. This format can be changed in TopAccess. For details, refer to the **TopAccess Guide**.
- If the same name has already been stored, a serial number (-001, -002...) will be automatically added to the end of the file name and stored.

**8** When the copy confirmation screen appears, press [YES] to store and print the document. If you want to store the document without printing it, press [NO].

COPY	STORAGE	SETTINGS , 🙀	TEMPLATE
CONFIRMATION			? 1
	Print this docum	ient?	
	YES	NO	
	(b)	1	
		CANCEL	]
		2011/	JOB STATUS

**9** Press the [START] button on the control panel.



#### Copying the next original

Depending on how the original is set, the confirmation screen to copy next the original may be displayed. Repeat the procedure below as many times as necessary. When the scanning of the last page of the original finishes, press [FINISHED].

- When the original is set on the glass, place the next original and press [YES]. When you press the [START] button on the control panel, scanning will start.
- When the original is set on the RADF (Reversing Automatic Document Feeder)\* in the SADF (single feed mode), scanning will start when the next original is set. (You do not need to press any key.)
   \* The RADF is optional.



#### • Deleting scan jobs

Follow the procedure below to stop the scanning of the documents (delete scan jobs).

- 1) Press [JOB STATUS].
- 2) On the job status menu, display the scan job list.
- 3) Select the job you want to delete, and then press [DELETE].
- 4) The delete confirmation screen appears. Press [DELETE].

For details of deleting scan jobs, refer to the Scanning Guide.

## Scanning to e-Filing


You can scan and store documents in e-Filing. When you import an original as an image into a client computer, it is recommended to store the document using Scan to e-Filing.

To use this, the scanning function is required.

## **1** Place the original(s).

For details of placing original(s), refer to the Copying Guide.

**2** Press the [SCAN] button on the control panel.



## 3 Press [e-FILING].

Scan Select Menu!!	SETTINGS , 😭	TEMPLATE
e-FLNG	🖳 E-MAL 🔪 USB 🗼	ELACE 2004
Destination	File Name File Format	PREVIEW
		SCAN
	2011/	05/10 JOB STATUS

#### Tip


Set [SCAN SETTING] and check [PREVIEW] as necessary. These operations are the same as the one of other scanning functions. For details of the operation, refer to the **Scanning Guide**.

#### Note

[PREVIEW] can be selected only when any of the following models is used.

- ES9455 MFP (only when a hard disk is installed)
- ES9475 MFP Series

4 Select the box or folder in which you want to store the documents. Change the document name as necessary, then press [OK].



The instructions of the operating procedure as to selecting a box/folder and changing a document name are omitted, because they are the same as those for copying and storing to e-Filing. P.17 "Copying and storing to e-Filing"

## 5 Press [SCAN].

	elect Menu‼ ress SCAN to start scanning.			
	US SCAN	E-MAL	🏷 USB	CAN     CON     C
	Destination	File Name	File Format	A PREVIEW
1	🐞 UserBox 0 1	DOC110510		

When the original is set on the RADF (Reversing Automatic Document Feeder)<sup>\*</sup>, pressing [CONTINUE] on the screen during scanning can start the scanning of another original after the current one.

- P.24 "Scanning the next original"
- The RADF is optional.


#### Note

The acceptable number for reserving scanning jobs differs depending on the settings. If the reserved jobs exceed the corresponding number, the full reservation message will be displayed. In this case, wait until the reserved scanning jobs are reduced or delete unnecessary reservations (scanning jobs) as described below.

#### • Scanning the next original

When the original is set on the glass or [CONTINUE] is pressed during scanning on the RADF, the confirmation screen for the next original will be displayed.

In either case, when you set the next original and press [SCAN], it will be scanned. Follow this procedure as many as times as necessary. When all of the scanning is finished, press [JOB FINISH].



- You can change the scan setting by pressing [SCAN SETTING].
- · You can cancel the reservation of the scanned data by pressing [JOB CANCEL].

#### • Deleting scan jobs

Follow the procedure below to stop the scanning of the documents (delete scan jobs).

- 1) Press [JOB STATUS].
- 2) On the job status menu, display the scan job list.
- 3) Select the job you want to delete, and then press [DELETE].

4) The delete confirmation screen appears. Press [DELETE].

For details of deleting scan jobs, refer to the Scanning Guide.

2

## **Deleting Documents**

You can delete documents in e-Filing using the control panel of this equipment.


#### Note

e-Filing is not designed for saving documents permanently. Delete unnecessary documents immediately.

#### Tip

If you delete a folder or box, all the documents in the folder or box are deleted as well. P.31 "Deleting user boxes/folders" (Operating with this equipment) P.47 "Deleting user boxes and folders" (Operating with a client computer)

#### Press the [Filing Box] button on the control panel.






#### Select a box or folder that contains a document you want to delete.



The instructions of the operating procedure as to selecting a box/folder are omitted, because they are the same as those for printing an entire document. P.12 "Printing an entire document" **3** Select the document you want to delete and then press [DELETE].



Tip

Press Delta to preview thumbnail images of the documents. Select the desired one and press [OPEN] to display its contents. Press to return to the list.

**4** When the confirmation screen appears, press [DELETE] to delete the selected document.

🔋 e-FILIN	G	☆ TEMPLATE 🔎	?
P			
Folder01 DOC110 DOC110	ATTENTION Are You sure you want to delete this document? DELETE CANCEL	Pages 1	1 / 1
▲ RETURN	Univer	\$	
PRINT	BOX SETTING		
		2011/05/10 JOB ST 07:22	ATUS 🗼

You can cancel the deletion of the selected document by pressing [CANCEL].

## **Managing User Boxes/Folders**

You can manage user boxes and folders in the e-Filing using the control panel of this equipment.

- P.27 "Creating user boxes"
- P.29 "Editing user boxes"
- P.31 "Deleting user boxes/folders"

Tip

Folders can be created and edited using a client computer.


P.44 "Creating user boxes and folders"

P.50 "Renaming user boxes and folders"

P.54 "Modifying and displaying user box and folder properties"


## Creating user boxes

You can create user boxes (up to 200).





**2** Press the [BOX SETTING] tab, select an unregistered button numbered from "001" to "200", then press [SETUP].



Press 🔿 or 🔽 to switch the pages. You can also directly specify the box number (3-digit) the using digital keys.

**3** Press [BOX NAME] and enter the box name.

BOX SETUP		MPLATE 2
Enter BOX name and	Password	
	Box No : 011 BOX NAME SSWORD RETYPE PASSWORD	
	CANCEL	ОК
	07:2	JOB STATUS

#### • Entering box name

Press [BOX NAME]. The on-screen keyboard is displayed. Key in the box name (up to 32 characters) using the keyboard and the digital keys, then press [OK]. However, the following one-byte characters cannot be used. A space or period cannot be used at the beginning or end of the name. If these characters are keyed in, an error message informing you of the invalid character used is displayed. "# % & ' = | { } \* < > ? []; :/\,

UserBox11_
Basic   Back Space Clear
* 1 2 3 4 5 6 7 8 9 0 - + Q W E R T Y U I O P [] \ A S D F G H J K L : * Z X C V B N M , . / @ Copp Shift Space

For details of the on-screen keyboard, refer to the Quick Start Guide.

**4** Enter the password in the [PASSWORD] and [RETYPE PASSWORD] boxes, then press [OK].

BOX SETUP		☆	TEMPLATE
Enter BOX name and P	assword.		
ſ	Box No : 011 BOX NAME UserBox 11 PASSWORD	*****	
	RETYPE PASSWORD	******	
	V	CANCEL	OK

- Press [PASSWORD] and then [RETYPE PASSWORD]. Enter the password using the digital keys or the onscreen keyboard. You can also create a user box without setting a password. In this case, all users can access the user box as well as the public box.
- If you press the [CLEAR] button on the control panel, the value entered in the currently selected box can be deleted.


#### Notes

- If the entered password does not meet the Password Policy, a warning message appears. Enter the correct one.
- For details of the Password Policy, refer to the TopAccess guide.
- The password input is displayed in the blank symbols.

## Editing user boxes

You can change the registered user box name and password.

#### Press the [Filing Box] button on the control panel.



**2** Press the [BOX SETTING] tab, select the user box that you want to edit, and then press [EDIT].



Press 
or v to switch the pages. You can also directly specify the box number (3-digit) the using digital keys.

#### Password entry

When the password has been set to the selected user box, the password entry screen is displayed. In this case, press [PASSWORD], enter the password using the digital keys or the on-screen keyboard, and then press [OK].

	BOX MODIFY			👷 TEMPLA	TE <b>?</b>
	Enter BOX Password.				
		BOX NUMBER	: 011		
		BOX NAME	: UserBox11		
·		PASSWORD,	*****		
			C.	ANCEL	ĸ
				07:42	ŢŹ)ĔIJ

#### Tips

- · You can also enter the administrator password to open the user box instead of the password.
- The password input is displayed in the blank symbols.
- **3** Change [BOX NAME] / [PASSWORD] / [RETYPE PASSWORD] as necessary, and then press [OK].

Enter BOX name and Password BOX NUMBER: : 011 BOX NAME UserBox 11		G ☆ TEMPLATE ↓ 2
	Enter BOX name a	and Password
PASSWORD ****** RETYPE PASSWORD ******		BOX NAME, UserBox11 PASSWORD

The instructions of the operating procedure of [BOX NAME] / [PASSWORD] / [RETYPE PASSWORD] settings are omitted, because they are the same as those for creating user boxes.


## Deleting user boxes/folders

You can delete user boxes and folders.

#### Note

If you want to delete a folder or a box, all documents in the folder or the box are deleted as well.

Press the [Filing Box] button on the control panel.





#### Follow the procedure below to delete user boxes and folders.

#### • Deleting user boxes

Press the [BOX SETTING] tab, select the user box you want to delete and then press [DELETE].



The instructions for the operating procedure for selecting user boxes are omitted, because they are the same as those for editing user boxes.

P.29 "Editing user boxes"

#### Deleting folders

Press the [PRINT] tab, select the folder you want to delete and then press [DELETE].

📦 e-FILING		😭 TEMPL	ATE 🔎 ?		
► 011 UserBox11		E			
Document / Folder Name	Date,Time	Paper	Pages		
Folder01	10, 07:47				
DOC110509	10, 07:48	A4	1 1		
DOC110510	10, 07:48	A4	3 1		
PRINT BOX SETTING					
		2011/05/10 07:48	JOB STATUS 📡		
2					

The instructions for the operating procedure for selecting folders is omitted, because it is the same as the one of printing an entire document.

P.12 "Printing an entire document"

## **3** When the confirmation screen appears, press [DELETE] to delete the selected box/ folder.



You can cancel the deletion of the selected box/folder by pressing [CANCEL].

# 3

# **OVERVIEW OF e-Filing WEB UTILITY**

This chapter provides an overview of the e-Filing web utility features.

Before Using the e-Filing Web Utility	34	
Getting Started With the e-Filing Web Utility		
Logging in as a user		
Logging in as a system administrator		
About the Main Tabs		
[Documents] tab		
[Preferences] tab	40	
[Administration] tab	41	
Log-in link	10	

## Before Using the e-Filing Web Utility

Before using the e-Filing web utility, check the following items on your computer. P.34 "System requirements"

## System requirements

The e-Filing web utility works with the following browsers for the Microsoft Windows operating system:

- Microsoft Internet Explorer 6.0 or later (Internet Explorer 7.0 or later when IPv6 is used)
- Firefox 3.5 or later
- The minimum display resolution required for these browsers is 800 x 600.
- When using Internet Explorer, the Privacy setting must be set to Medium on the browser. Do not set Block All Cookies or High for the Privacy function. For instructions on the Privacy setting, see the following procedure.
- Disable the popup block function of the Web browser. For instructions on how to set the popup block function, refer to the HELP for the Web browser you are using.

e-Filing does not support access from Safari.

#### How to set the privacy settings in Internet Explorer

When you are using Internet Explorer, make sure that the Privacy setting is correct as follows.

## **1** Launch Internet Explorer and select [Internet Options] in the [Tools] menu.

	ools <u>H</u> elp		
☆ Favorites │ ☆ @ Sugge: @ TopAccess	Delete Browsing History         Cttl+Shift+De           InPrivate Browsing         Ctrl+Shift+F           Diagnose Connection Problems         Reopen Last Browsing Session		
	InPrivate Filtering Ctrl+Shift+I InPrivate Filtering Settings		
Device	Pop-up Blocker SmartScreen Filter Manage Add-ons	ation	Counter
Device	Compatibility View Compatibility View Settings		Ready
	Subscribe to this Feed Feed Discovery Windows Update	F	annen ann
	Developer Tools F1	2	CODEND-1
	OneNote Linked Notes Lync Click to Call		2048 MB 512 MB

The [Internet Options] dialog box appears.

- 2
- Display the [Privacy] tab and move the slider to "Medium" and click [OK].

Internet Opti	ons	? ×
General Settings -	curity Privacy Content Connections Programs	Advanced
	Medium - Blocks third-party cookies that do not have a comp privacy policy - Blocks third-party cookies that save information the used to contact you without your explicit concer - Restricts first-party cookies that save information - an be used to contact you without your implicit cor	at can It that
Pop-up Blo		ault
InPrivate	Do not collect data for use by InPrivate Filtering Disable toolbars and extensions when InPrivate Bro starts	wsing
	OK Cancel	Apply

The Privacy setting is saved.

## **3** Exit from Internet Explorer and launch it again before accessing e-Filing.

## Note

Exit from Internet Explorer after accessing the e-Filing web utility. To log off from the e-Filing web utility in the user mode, click the Log-out link and then exit from Internet Explorer.

3

## Getting Started With the e-Filing Web Utility

This section describes how to launch and exit from the e-Filing web utility. The way to launch the utility differs depending on whether you log in as a user or a system administrator.

P.36 "Logging in as a user"
 P.37 "Logging in as a system administrator"

## Logging in as a user

There are two ways to access the e-Filing web utility:

- Click the e-Filing web utility link in the TopAccess web site.
- Enter the e-Filing web utility URL in the address field of your Web browser.

The e-Filing web utility URL is: http://[IP address]/?MAIN=EFILING

The [IP address] portion will be the IP address of this equipment. You can also use the DNS name of this equipment instead of the IP address.

For example, the IP address of this equipment is 192.168.1.2 http://192.168.1.2/?MAIN=EFILING For example, the DNS name of this equipment is mfp-00000236 http://mfp-00000236/?MAIN=EFILING

## Note

If SSL is enabled for the HTTP network service, the e-Filing web utility will also be accessed by using SSL.

When the User Management Setting has been enabled, the log-in page will be displayed when accessing the e-Filing web utility URL. In that case, please enter your User Authentication user name and password to log in to the main page of the e-Filing Web Utility.

Login with your TopAccess U	ser Name and Password.	
User Name	User01	
Password	•••••	
Domain	dept01 💌	
	Login	
	<u>Top   Help  </u>	

## Notes

- If you enter an invalid authentication password several times to log into the OKI MFP, you may not be able to log in for a certain period since it will be regarded as an unauthorized access.
- · The password input is displayed in the blank symbols.

Tips

- Users can launch the e-Filing web utility to use its functions.
- Access to the e-Filing web utility will be timed out according to the Session Timer setting in the WEB General Setting of TopAccess.
- To use the administrator's functions of the e-Filing web utility, you must log in as a system administrator after accessing it.

P.37 "Logging in as a system administrator"

## ■ Logging in as a system administrator

To log in as a system administrator, follow the steps below after launching the e-Filing web utility.

#### Note

"System administrator" and "User with an administrator privilege" are defined as follows in this manual.

- System administrator:
- User with the administrator role
- User with an administrator privilege: User whose ID is "Admin"

**1** Click the Log-in link located at the upper right of the page.

	11	Do	Documents		Preferences	Login
(11) (11)				51		

The Administrator Log-in page is displayed.

## 2 Enter the administrator password in the [Password] box and click [Login].

Selectronic Filing
Administrator Login
Password
Login Cancel
Top   Help

The [Administration] tab appears in the main tabs.

#### Notes

- If you enter an invalid authentication password several times to log into the e-Filing web utility in the administrator mode, you may not be able to login for a certain period since it will be regarded as an unauthorized access.
- To log off from the e-Filing web utility in the administrator mode, click the Log-out link and be sure to close your web browser to prevent unauthorized access by other users.

Tips

- The administrator password is the same as the password that has been set in the TopAccess or touch panel display for the administrator. The default administrator password is "123456" if you have not changed it.
- · The password input is displayed in the blank symbols.

## About the Main Tabs

The user interface of the e-Filing web utility consists of three main tabs located in the upper-right corner of the web browser's window: the [Documents] tab, [Preferences] tab, and [Administration] tab.



These main tabs enable you to display and work with your documents, set up viewing preferences, and perform administrative functions.

P.38 "[Documents] tab"


P.40 "[Preferences] tab"


P.41 "[Administration] tab"

In addition, the Log-in link is located to the right of the main tabs which allows you to log in as a system administrator.

## [Documents] tab

The [Documents] tab is the default page and is available to all users. It consists of the Folders and Document frame, the Menu Bar, and the Contents frame.





#### 4) Contents Frame

The Contents frame displays the documents or pages with which you are working. There are also document control buttons located below the menu bar. You can use these buttons to change the document status between the View mode and Edit mode, and use the Contents frame to print and edit your documents.

#### Tip

For more information about the document control buttons, see the following section:  $\square$  P.88 "About the Document Control Buttons"

## [Preferences] tab

The [Preferences] tab is available to all users. It allows you to make the default condition for document viewing and the number of thumbnail images displayed on the screen.

	Selectronic Filing Documents Preferences Login
	Preferences
-	Default Document View. Thumbnail view
2 — 3 —	Load 8 ▼ thumbnails per view. Display the progress bar.
4 — 5 —	Save Reset
	Тор   Нејр

#### 1) Default Document View

You can select the Thumbnail or List view. The system displays your documents by the selected view until you choose another option from the View menu. The default is the Thumbnail view.

#### 2) Load [number] thumbnails per view.

Use the drop-down list box to select the number of thumbnail images displayed on the screen as 4, 8 or 12. The default is 8.

#### 3) Display the progress bar.

Select the [Display the progress bar.] check box to display the progress bar when copying, cutting, or pasting the documents or pages, deleting pages, or saving documents.

4) [Save]

Click this button to apply your new settings.

#### 5) [Reset]

Click this button to restore the default settings.

## [Administration] tab

The [Administration] tab allows the system administrator to manage the data in e-Filing. The [Administration] tab is only visible if you are logged on as the system administrator.

- The [Administration] tab has the following subtab:
- P.41 "[Box Management] subtab"

#### Tip

An administrator can also set up the e-Filing notifications by using TopAccess in the administrator mode. For more information about setting up the notifications for e-Filing, refer to the *TopAccess Guide*.

## [Box Management] subtab

This subtab enables you manually to delete user boxes that are no longer required or have become corrupted. Use this feature to restore the available hard disk space.

You can also unlock user boxes which have been locked by incorrect password entries.

e-Filing Disk Space Available : 10142 MB Stored Data Box	Data Type	Data Size	-	
				emarks
Dox	Shared File	97 MB	R	emarks
Delete Unlock				
Box Number	Box Name		Used capacity	Statu
001	User01		57 MB	
001	User01 User02		57 MB 5 KB	
002	User02		5 KB	
002     003	User02 User03		5 KB 5 KB	
<ul> <li>002</li> <li>003</li> <li>004</li> </ul>	User02 User03 User04		5 KB 5 KB 40 MB	

#### 1) e-Filing Disk Space Available

This item displays the available hard disk space for storing the e-Filing data.

## 2) Box Number / Box Name / Used capacity / Status

This item displays a list of all user boxes. When you click a box number or box name link, the Box Properties window opens and you can see the detail properties of the box. If the user box is locked, the lock status is displayed in the results. To delete or unlock a user box, select the check box on the left of each property, and then click [Delete] or [Unlock].

#### 3) [Delete]

Click this button to delete the selected boxes. Before doing so, first select the check boxes of the user boxes that you want to delete.

Tips

- You cannot delete the public box.
- For instructions on how to erase user boxes, see the following section:
   P.114 "Erasing boxes"

#### 4) [Unlock]

Click this button to unlock the selected boxes. Before doing so, first select the check boxes of the user boxes that you want to unlock.

Tip

For instructions on how to unlock the user boxes, see the following section:

## Log-in link

The Log-in link that is displayed next to the main tabs allows you to log in as a system administrator.

P.42 "Administrator log-in page"

You can perform the administrative function from the [Administration] tab that will be displayed after you log in as a system administrator.

P.41 "[Administration] tab"

## Administrator log-in page

You must enter the system administrator password to log in as an administrator.

Selectronic Filin	ng
A desiristant sa ha sis	
Administrator Login	
Password	•••••
Login Cancel	
	Administrator Login

## 1) Password

Enter the system administrator password that is same as the administrator password on the touch panel display and TopAccess.

## 2) [Login]

Click this button to log in as a system administrator.

## 3) [Cancel]

Click this button to cancel login and return to the main page.

# HOW TO MANAGE USER BOXES/FOLDERS

4

This chapter provides instructions on how to manage user boxes and folders by using the e-Filing web utility.

Managing User Boxes and Folders	. 44
Creating user boxes and folders	
Deleting user boxes and folders	
Renaming user boxes and folders	
Modifying and displaying user box and folder properties	

## Managing User Boxes and Folders

The e-Filing web utility provides two box types: the public box and user box. Each user can create his or her own user box, and also create one level of folder in each box.

This section explains the following operations:

- P.44 "Creating user boxes and folders"
- P.47 "Deleting user boxes and folders"
- P.50 "Renaming user boxes and folders"
- P.54 "Modifying and displaying user box and folder properties"

т	ï	n	
1	ľ	Р	

For a detailed explanation of the public box and user box, see the following page:  $\square$  P.6 "e-Filing Features"

## Creating user boxes and folders

Each user can create his or her own user box, and also protect the box with a password, if required.

P.44 "Creating user boxes"

P.45 "Creating folders"

## Creating user boxes

This operation allows you to create up to 200 user boxes and protect each box with a password.

Tip


You can also create user boxes from the control panel. For instructions on how to create user boxes from the control panel, see the following page:

P.27 "Creating user boxes"

## Click the [Documents] tab.

The [Documents] tab page is displayed.

**2** Make sure that you are selecting "e-Filing" in the Document frame, and select [New Box] from the [File] menu.



The New Box window appears.

## **3** Define the box properties as required and complete the operation.

- Select a box number in the [Box Number] box. Users cannot select existing box numbers in the [Box Number] box. Only undefined box numbers appear in this drop-down list box.
- 2) Enter the box name in the [Box Name] box. Box names can consist of any ASCII characters except: \/ <> " % & = '; : \* ? | # [] { }. Do not use a space or period at the beginning or end of the name. The maximum size of a box name is 32 characters.
- 3) If you want to protect the box with a password, enter one in the [Box Password] and [Confirm Password] boxes. The password input is displayed in the blank symbols.

4) Click [OK].

New Box	
*Required	
Box Number:	
* Box Name:	User08
Box Password:	····· \vdots_2
Retype Password:	•••••
OK Cancel	3

The created user box appears in the Document frame.

## Tip

Users can configure advanced properties for each box such as how long the box will retain documents, and Email notification features.

P.54 "Modifying box properties"

## **Creating folders**

This operation allows you to create up to 100 folders in each box.

## Note

Only single-level folders can be created in each box. You cannot create subfolders in the folders.

## Click the [Documents] tab.

The [Documents] tab page is displayed.

## **2** In the Document frame, select the box where you want to create a folder.



If you select a box that is protected with a password, the Password Authentication 3 window appears. Enter the password in the [Box Password] box and click [OK].

Password Authentication	
Box Number :	001
Box Name :	User01
Box Password :	
OK Cancel	

#### Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- The password input is displayed in the blank symbols.

т		-
	н	r.

You can also enter the password of a user with an administrator privilege in [Box Password].

## 4 Click the [File] menu and select [New Folder].

Selectronic Filing						
	File	Edit	View	Layout		
Document           e-Filing           ■ Public Box           ■ M 001 User01           ■ M 002 User02           ■ M 003 User03           ■ M 004 User04           ■ M 005 User05           ■ M 005 User06           ■ M 007 User07	Upload Test P Print D Proper	e Docume I Archived rint locument	I Document			

The New Folder window appears.



Enter the folder name in the [Name] box and click [OK].

New Folder Name: Folder01	)
OK Cancel	-

The created folder appears under the selected box in the Document frame.

## Note

Folder names can consist of any ASCII character except \ / < > " % & = '; : \* ? | # [] { }. Do not use a space or period at the beginning or end of the name. The maximum size of a folder name is 64 characters.

## Deleting user boxes and folders

This operation allows you to delete user boxes and folders.

- P.47 "Deleting user boxes"
- P.48 "Deleting folders"

Tip

When the box has been protected with a password, you must enter it to delete the box and folders. Users with an administrator privilege can delete all user boxes and folders by using their password.



Folders in the public box can be deleted, although you cannot delete the public box itself.

## Deleting user boxes

This operation allows you to delete user boxes. If a user box is deleted, all folders and documents in the box are also deleted.

Tip

You can also delete user boxes from the control panel. For instructions on how to delete user boxes from the control panel, see the following page:

P.25 "Deleting Documents"

## Click the [Documents] tab.

The [Documents] tab page is displayed.

## **2** In the Document frame, select the user box that you want to delete.



**3** If you select a user box which is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].

Password Authentication	
Box Number :	001
Box Name :	User01
Box Password :	
OK Cancel	


Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- · The password input is displayed in the blank symbols.

Tip

You can also enter the password of a user with an administrator privilege in [Box Password].

▲ Click the [Edit] menu and select [Delete].



The confirmation message dialog box appears.

<b>ЭК]</b> .
rom webpage
Do you want to delete the item(s)? 001 User01
OK Cancel

The selected box is deleted.

## Deleting folders

This operation allows you to delete folders in the public box and user boxes. If a folder is deleted, all documents in the folder are also deleted.

Tip

5

You can also delete folders from the control panel. For instructions on how to delete folders from the control panel, see the following page:


P.31 "Deleting user boxes/folders"

## Click the [Documents] tab.

The [Documents] tab page is displayed.

1
/

In the Document frame, select the box containing the folders that you want to delete.



**3** If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].

Password Authentication	
Box Number :	001
Box Name :	User01
Box Password :	
OK Cancel	

All folders and documents in the box are displayed in the Contents frame.

#### Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- · The password input is displayed in the blank symbols.

Tip

You can also enter the password of a user with an administrator privilege in [Box Password].

## 4 Select the check boxes of the folders that you want to delete and select [Delete] from the [Edit] menu.

Selectronic Filing	g			
	File	Edit	View	Layout
Document		Select A Invert St Cut Copy Paste Delete		

The confirmation message dialog box appears.

#### Note

You can also delete a folder by selecting the folder in the Document frame, clicking on the [Edit] menu and selecting [Delete]. In that case, make sure that no documents are selected in the Contents frame. If any documents are selected, they will be deleted instead of the selected folder.

## 5 Click [OK].

Message fr	om webpage Do you want to delete tl Folder01	he item(s)?
	ок р	Cancel

The selected folders are deleted.

## Renaming user boxes and folders

This operation allows you to rename the user boxes and folders.

- P.50 "Renaming user boxes"
- P.52 "Renaming folders"

## Tip

When the box has been protected with a password, users must enter it to rename the box or folders. Users with an administrator privilege can rename all user boxes and folders by using their password.

## Note

You can rename folders in the public box, but cannot rename the public box itself.

## Renaming user boxes

## Note

Do not turn off the power of the equipment when changing the box name. All folders and documents in the box will be lost if the power is turned off while the system is saving a new name.

## Tip


Users can rename user boxes from the control panel. For instructions on how to rename user boxes from the control panel, see the following page:

P.29 "Editing user boxes"

## Click the [Documents] tab.

The [Documents] tab page is displayed.

## In the Document frame, select the user box that you want to rename.



**3** If you select a user box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].

Password Authentication	
Box Number :	001
Box Name :	User01
Box Password :	
OK Cancel	

## Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- The password input is displayed in the blank symbols.

Tip

You can also enter the password of a user with an administrator privilege in [Box Password].

**4** Click the [File] menu and select [Rename].

Sectronic Filing	g				
	File	Edit	View	Layout	
Document	Upload Test Pr Print D Proper Send E	e I Turne Archived rint ocument ties	Document		

The Rename Box window appears.

## Note

Make sure that no folder or document is selected in the Contents frame. If a folder or document is selected, it will be renamed instead of the selected box.



## 5 Edit the name in the [Name] box and click [OK].



The confirmation dialog box appears.

## Note

Box names can consist of any ASCII characters except \ / < > " % & = ' ; : \* ? | # [ ] { }. Do not use a space or period at the beginning or end of the name. The maximum size of a box name is 32 characters.

#### Click [OK]. 6

Message from webpage
Do you want to rename the item?
OK Cancel

The selected box is renamed.

## □ Renaming folders

## Note

Do not turn off the power of the equipment when changing the folder name. All documents in the folder will be lost if the power is turned off while the system is saving a new name.

Click the [Documents] tab.

The [Documents] tab page is displayed.

**2** In the Document frame, select the box containing the folder you want to rename.

Selectronic Fili	ng			
	File Edit	View	Layout	
Document	📳 e-Filing (8 i	items)		
	Ŷ			
	🔲 Public B	ox	🔲 001 User01	

**3** If you select a box that is protected with a password, the Password Authentication window appears. In this case, enter the password in the [Box Password] box and click [OK].

All folders and documents in the box are displayed in the Contents frame.


## Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- The password input is displayed in the blank symbols.

Tip

You can also enter the password of a user with an administrator privilege in [Box Password].

4 Select the check box of the folder that you want to rename and select [Rename] from the [File] menu.



The Rename Folder window appears.

#### Notes

- Do not select several folders at the same time. You can only rename one folder at a time.
- You can also rename a folder by selecting the folder in the Document frame, clicking on the [File] menu and selecting [Rename]. In that case, make sure that no document is selected in the Contents frame. If a document is selected, it will be renamed instead of the selected folder.



Rename F	older
Name :	Folder01
ОК	Cancel


The confirmation dialog box appears.

## Note

Folder names can consist of any ASCII character except  $/ < > " % & = '; : * ? | # [] { }. Do not use a space or period at the beginning or end of the name. The maximum size of a folder name is 64 characters.$ 



#### Click [OK].



The selected folder is renamed.

## Modifying and displaying user box and folder properties

This operation allows you to display and modify the properties of user boxes such as the box password and maintenance period to automatically delete documents, and Email notification settings. This operation also allows you to view and confirm the folder properties.

P.54 "Modifying box properties"

P.57 "Displaying folder properties"

#### Tip

When the box has been protected with a password, you must enter it to modify the box properties. Users with an administrator privilege can modify all user box properties and public box properties by using their password.

## Modifying box properties

## Notes

- If you want to modify the public box properties, you must first log in as the system administrator.
- You cannot modify the password of a box that any user is currently accessing.

## Click the [Documents] tab.

The [Documents] tab page is displayed.

**2** In the Document frame, select the user box whose properties you want to display and edit.

Selectronic Filing	Selectronic Filing								
	File	Edit	View	Layout					
Document	📳 e-F	iling (8 ite	ms)						
				â					
	- F	Public Bo:	×	🗖 001 User01					

**3** If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].

Password Authentication	
Box Number :	001
Box Name :	User01
Box Password :	
OK Cancel	

## Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- · The password input is displayed in the blank symbols.



You can also enter the password of a user with an administrator privilege in [Box Password].

**4** Click the [File] menu and select [Properties].

Selectronic Filing	g			
	File	Edit	View	Layout
Document         e-Filing         Public Box         image: point of the second s	Upload A Test Prin Print Dor Properti Page Pro Send Em	der Documen Irchived E nt cument	t locument 	

4

The Box Properties window appears. In the Box Properties window, you can see the box properties.

## **5** If you want to edit the box properties, click [Change Properties].


Box Properties	
	001 User01
Contains:	0 File(s) 1 Folder(s)
Preservation Period for Documents :	
Email Address for Notification :	
Created :	2011.05.10 09:03:22
Modified :	2011.05.10 09:03:22
OK Change Properties	$\mathbf{k}$

The Change Box Properties window is displayed.

#### Tip

If you do not need to change the box properties, press [OK] on the above screen to complete the operation.

6 Specify the following items as required and press [Save].



**Change Box Password** — Select this check box to edit the box password. When you select this check box, enter the password in the [Old Password], [New Password], and [Confirm New Password] boxes.

- Old Password Enter the current box password. This option is enabled only when you select the [Change Box Password] check box.
- New Password Enter the new box password. This option is enabled only when you select the [Change Box Password] check box.
- Confirm New Password Enter the new box password again. This option is enabled only when you select the [Change Box Password] check box.

#### Tip

If you forget the old password, you can enter the administrator password in the [Old Password] box instead of it.

**Delete document automatically** — Select this check box to automatically delete the documents in this box. When you select this check box, enter the number of days in the [Preservation Period for Documents] box.

Preservation Period for Documents — Enter the number of days that the documents will be preserved. The
documents will be deleted after the specified number of days have passed. If you set this period to 1 day, the
document will be deleted automatically 24 hours later.

## Note

If a document is automatically deleted by the [Delete document automatically] function, the delete history is not stored in the log.

For details of the logs, refer to the TopAccess Guide.

**Send Email when an error occurs** — Select this check box to send a notification message to the specified Email address when an error occurs. When you select this check box, enter the Email address in the [Email Address] box.

**Send Email when job is completed** — Select this check box to send a notification message to the specified Email address when a job is complete. When you select this check box, enter the Email address in the [Email Address] box.

Advance automatic delete notification — Select this check box to enable an Email notification message to be sent to the specified Email address 3 days before it automatically deletes the documents. When you select this check box, enter the Email address in the [Email Address] box.

• Email Address — Enter the Email address to which the notification will be sent.

#### Tip

When the options "Send Email when an error occurs" and "Send Email when job is completed" are enabled, you are notified of whether or not the following e-Filing operations are successfully completed.

- Scan to e-Filing
- Copy to e-Filing
- Print to e-Filing
- Fax/Internet Fax Received Forward to e-Filing
- e-Filing to Print
- e-Filing to Email

An administrator can configure the e-Filing notification setting in the TopAccess [Administration] tab -Maintenance - Notification page. For more information, refer to the **TopAccess Guide**.


## **7** Click [OK] to close the Box Properties window.

8	001 User01	
Contains:	0 File(s) 1 Folder(s)	
Preservation Period for D	Documents : -	
Email Address for Notific	ation : -	
Created :	2011.05.10 09:03:22	
Modified :	2011.05.10 09:04:43	
OK Chang	e Properties	

## Displaying folder properties

You can only view and confirm the folder properties. No operation to modify the folder properties is available.

- 1 Click the [Documents] tab. The [Documents] tab page is displayed.
- 2 In the Document frame, select the box containing the folder whose properties you want to display.



**3** If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].

Password Authentication	
Box Number :	001
Box Name :	User01
Box Password :	
OK Cancel	

All folders and documents in the box are displayed in the Contents frame.

## Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- The password input is displayed in the blank symbols.

Tip

You can also enter the password of a user with an administrator privilege in [Box Password].

4 Select the check box of the folder with the properties that you want to view and select [Properties] from the [File] menu.

Sectronic Filing	g			
	File	Edit	View	Layout
Document ■ e-Filing ■ Public Box ■ 001 User01 ■ 002 User02 ■ 003 User03 ■ 004 User04 ■ 005 User05 ■ 006 User06 ■ 007 User07	Upload Test P	older ne Docume I Archived Irint Document	2	

The Folder Properties window appears. In the Folder Properties window, you can view the folder properties.

#### Notes

- Do not select several folders at the same time. You can only view the properties of one folder at a time.
- Users can also display the properties of a folder by selecting the folder in the Document frame, clicking on the [File] menu and selecting [Properties]. In that case, make sure that no document is selected in the Contents frame. If a document is selected, its properties are displayed instead of the selected folder.

## **5** Click [OK] to close the Folder Properties window.

	Folder01	
Location :	e-Filing/User01/Folder01	
Contains :	0 File(s)	
Created :	2011.05.10 09:03:38	
Modified :	2011.05.10 09:03:38	
OK		

The following information is displayed in the Folder Properties window:
Location — Displays the directory where the folder is located.
Contains — Displays the number of files the folder contains.
Created — Displays the date and time the folder was created.
Modified — Displays the date and time the folder was last modified.

# 5

# **MANAGING DOCUMENTS**

This chapter provides instructions on how to manage documents by using the e-Filing web utility.

How To Manage Documents	60
Displaying documents	60
Renaming documents	
Deleting documents	63
Printing documents	
Storing documents	
Archiving documents	
Sending Email	78

## How To Manage Documents

The e-Filing web utility allows you to manage the documents stored in the e-Filing system. This section explains the following operations:

- P.60 "Displaying documents"
- P.61 "Renaming documents"
- P.63 "Deleting documents"
- P.64 "Printing documents"
- P.70 "Storing documents"
- P.73 "Archiving documents"
- P.78 "Sending Email"

## Displaying documents

Two ways are available to view your document image files. The document view options are:

- Thumbnail view displays several files from a selected box, folder or several pages of the selected document. This is the default view. Use it to manage documents and files.
- P.60 "Using the thumbnail view"
  List view displays file names and properties in a tabular formation
- List view displays file names and properties in a tabular format. Use it to manage boxes and folders containing a large number of files.

P.61 "Using the list view"

## **Using the thumbnail view**

This is the default view, unless you choose a different one. It displays a small image of each file or folder (if you highlight a box or folder in the left frame) or each page (if you highlight a document in the left frame) with the file name or page number and a check box. Click the check boxes to select the files or pages that you want to move, copy, delete or print. To return to the thumbnail view, go to the [View] menu and select [Thumbnail].

Sectronic Filing	9				Documents I	Preferences	<u>Login</u>
	File Ed	lit. View	Layout	5 2 <i>4</i> 1 4 8	< < > >		
Document	🔓 DOC110	0510-001 (1/3)			Status :	View Edit	t
<pre></pre>	Quick Start	Guide	<ul> <li>Image: A state of the state of</li></ul>	Image: state stat			
			Top   Help				

## Using the list view

This view displays boxes, folders, or file names with the properties and check boxes in a list format. You may find it more convenient than the thumbnail view for managing boxes and folders that contain a large number of files. Click the check boxes to select a single file or multiple files that you want to move, copy, delete or print. To display your files by the list view, go to the [View] menu and select [List].

Sectronic Filing	g						Documents	Preferences	Log
	File Edi	t View	Layout		<b>R</b>	5 X 🖬 🖻	< < > >		
Document	🔓 DOC1105	510-001 (1/3)					Status : View	Edit	1
🛱 e-Filing 🗉 🏫 Public Box	Pages#			Format	Resolution	Image Size	Paper Size	Size	
🗆 🏄 001 User01	🔲 Pages	1		Сору	600 x 600	4867 x 6922	A4	6710 KB	
⊞ ☐ Folder01     ☐ DOC110510	🔲 Pages	2		Сору	600 x 600	4867 x 6922	A4	6506 KB	
DOC110510-001     main 200     main 20	Pages	3		Сору	600 × 600	4867 x 6922	A4	6306 KB	
4									

## Renaming documents

This operation allows you to rename the documents.


#### Note

Do not turn off the power of the equipment when changing the document name. The document will be lost if the power is turned off while the system is saving a new name.

## **1** Click the [Documents] tab.

The [Documents] tab page is displayed.

# **2** In the Document frame, select the box or folder containing the document you want to rename.



**3** If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].

Password Authentication	
Box Number :	001
Box Name :	User01
Box Password :	
OK N Cancel	

#### Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- · The password input is displayed in the blank symbols.

Tip

You can also enter the password of a user with an administrator privilege in [Box Password].

# **4** Select the check box of the document that you want to rename and select [Rename] from the [File] menu.

Sectoric Filing				
	File	Edit	View	Layout
Document a e-Fiing a g-Public Box b g-Public Box b g-Folder01 b DoC110510 c DoC110510 c DoC10510 c DoC10510-001 c DoC10510 c DoC10510-001 c DoC10510 c DOC10510	New Fo Open Renam Archive Upload Test Pr Print Do Proper Send Ei	Ider Arch 2	jt Document	Doction (Scan)

The Rename Document window opens.

## Tip

Users can also rename a document by selecting the document in the Document frame, clicking on the [File] menu and selecting [Rename]. In that case, even if you select the check boxes of pages in the Contents frame, e-Filing will only rename the selected document in the Document frame.



## Enter the document name in the [Name] box and click [OK].

Rename D	ocument
Name :	D0C110510
OK	Cancel

The confirmation dialog box appears.

## Note

Document names can consist of any ASCII characters except  $/ < > " % & = '; : * ? | # [] {}. Do not use a space or period at the beginning or end of the name. The maximum size of a document name is 64 characters.$ 

## 6 Click [OK].

Message fr	om webpage 📃
?	Do you want to rename the item?
	OK Cancel

The document is renamed.

## Deleting documents

This operation allows you to delete documents from the box or folder.

- **1** Click the [Documents] tab.
- The [Documents] tab page is displayed.
- 2 In the Document frame, select the box or folder containing the documents you want to delete.



**3** If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].

Password Authentication	
Box Number :	001
Box Name :	User01
Box Password :	
OK Cancel	


## Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- The password input is displayed in the blank symbols.

#### Tip

You can also enter the password of a user with an administrator privilege in [Box Password].

# 4 Select the check boxes of the documents that you want to delete and select [Delete] from the [Edit] menu.



The confirmation dialog box appears.

## Note

Users can also delete a document by selecting it in the Document frame, clicking on the [Edit] menu and selecting [Delete]. In that case, make sure that no pages are selected in the Contents frame. If any pages are selected, the alert message will be displayed because pages cannot be deleted in the View mode.

## 5 Click [OK].

Message fr	om webpage
?	Do you want to delete the item(s)? DOC110510
	OK Cancel

The documents are deleted.

## Printing documents

You can print documents and images from boxes and folders in the e-Filing web utility. The following two ways are available to print them:


- P.64 "Printing an entire document"
- P.67 "Selecting test print"

## Printing an entire document

This operation allows you to print the entire document with various print options selected.

- 1 Click the [Documents] tab.
  - The [Documents] tab page is displayed.

# 2 In the Document frame, select the box or folder containing the document that you want to print.



**3** If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].

Password Authentication	
Box Number :	001
Box Name :	User01
Box Password :	
OK Cancel	

#### Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- · The password input is displayed in the blank symbols.

Tip

You can also enter the password of a user with an administrator privilege in [Box Password].

# 4 Select the check box of the document that you want to print and select [Print Document] from the [File] menu.

Selectronic Filing				
	File	Edit	View	Layout
Document           e-Filing           ⊕ Public Box           ⊕ 01 User01           ⊕ 000 User01           ⊕ 000 C110510-001           ⊕ 000 User02           ⊕ 003 User03           ⊕ 004 User04           ⊕ 005 User05           ⊕ 006 User06           ⊕ 007 User07	Upload Test P Print I Prope Page I Send I	older ne I Archived Irint Jocument rties		Decritorio (Scan]

The Print window appears.

#### Note

You can also print a document by selecting it in the Document frame and [Print Document] on the [File] menu. However, you cannot print individual pages even if you select the check boxes of the pages displayed in the Contents frame. 5

Duplex:	None	Cover/Sheet Insertion:
Number of Copies:		Use Front Cover
Sort Copies		Source: Auto Select
Group Copies		Print Style: Do not print on page
Rotate Sort Copies		Use Back Cover
Paper Type:	Plain -	Source: Auto Select
		Print Style: Do not print on page
Department Code:		Insert Pages
Paper Source:	Auto Select 👻	Source: Auto Select
Destination:	Stacker 👻	Print Style: Do not print on page
Staple:	None -	Pages:
Binding:	None v	Interleave Pages
Hole Punch:	None -	Source: Auto Select
Page Number:		Duplicate
Position:	None 👻	Paper Type (Insert): Plain 👻
Initial Page:		Scheduled Print
Time Stamp:		Date & Time : Year Month Date Time
Position:	None -	
Image Shift:		
Position:	None -	
Shift Margin:		
Front:	0 - mm	
Back:	0 v mm	

**Duplex** — Select whether you want the document printed on both sides of the paper. When you want to print the document on both sides, select the Book option to print vertically in the same direction to be bound along the vertical side of the paper so that the pages can be turned over right and left, or the Tablet option to print with a vertical reversal to be bound along the horizontal side of the paper so that the pages can be turned over up and down.

Number of Copies — Enter the number of copies to be printed.

#### Note

The selectable range of the number of copies, 1 copy to 999 copies.

**Sort Copies** — Select this option to output the document separately for each copy.

Group Copies — Select this option to output the document separately for each page.

**Rotate Sort Copies** — Select this option to output the document by changing the output orientation of each copy. This option is enabled only when you enter more than one copy in the [Number of Copies] box. When this option is selected, the Destination option is automatically set to the inner finisher. To perform the Rotate Sort Copies, the portrait and landscape paper must be set in different trays.

#### Paper Type — Select the type of paper desired.

**Department Code** — Enter the 1 to 63-digit department code, if required. You must enter the department code to print a document if the department code is enabled on the equipment.

**Paper Source** — Select the paper feed source. Select a paper source that correlates with the printing size. **Destination** — Select the tray to which the document will be output.

**Staple** — Select whether the document is to be stapled or not. When you want to staple the document, select how it will be done.

## Note

If you enable the Staple option after enabling the Interleave Pages option, the latter will be automatically disabled.

**Binding** — Select this option to output the document folded or stapled at the center. You can set how the document is output.

- Center Fold The document is folded at the center.
- Saddle Stitch The document is double-stapled and folded at the center.



"Binding" is enabled only when the optional Saddle Stitch Finisher is installed.

**Hole Punch** — Select whether the document is to be hole-punched or not. When you want to hole-punch the document, select how it will be done.

**Page Number - Position** — Select whether the page numbers are to be printed on the pages. When you want to print the page numbers, select where it will be done.

**Page Number - Initial Page** — Enter the first number that applies to the first page of the document. When the Cover/Sheet Insertion - Use Front Cover option is enabled, the front cover is counted as the first page, and the first page of the document is counted at the second page.

**Time Stamp - Position** — Select whether the print time is printed on each page or not. When you want to print the time stamp, select where you want it to be done.

**Image Shift - Position** — Select whether the printed images are to be shifted or not. When you want to shift the printed images, select it to be done.

**Shift Margin - Front** — Select the width of the margin that is to be added to the side when the printed images are shifted.

**Shift Margin - Back** — Select the width of the margin that is to be added to the opposite side when the printed images are shifted.

**Cover/Sheet Insertion - Use Front Cover** — This option sets front cover printing which allows you to insert or print a cover on a sheet fed from a different tray than the Paper Source option. To enable front cover printing, select the check box and specify the location from where the cover sheet is to be fed and the print style to be used. **Cover/Sheet Insertion - Use Back Cover** — This option sets back cover printing which allows you to insert or print a cover on a sheet fed from a different tray than the Paper Source option. To enable back cover printing, select the check box and specify the location from where the cover sheet is to be fed and the print style to be used. **Cover/Sheet Insertion - Insert Pages** — This option sets sheet insertion printing which allows you to insert a sheet between pages, or print a specific page on a sheet fed from a tray other than the Paper Source option. This option is useful when you want to insert a blank sheet between chapters, or when you want to print chapter cover pages on different paper. To enable sheet insertion printing, select the check box and specify the location from where the cover sheet the check box and specify the location from where the the select is to be fed and the print style to be used. **Cover/Sheet Insertion - Insert Pages** — This option sets sheet insertion printing which allows you to insert a sheet between pages, or print a specific page on a sheet fed from a tray other than the Paper Source option. This option is useful when you want to insert a blank sheet between chapters, or when you want to print chapter cover pages on different paper. To enable sheet insertion printing, select the check box and specify the location from where the inserted sheets are to be fed and the print style to be used. Then enter the page numbers you want to

insert, separating them with commas if multiple pages are specified, in the [Pages] box. **Cover/Sheet Insertion - Interleave Pages** — This option sets the interleaving page feature that is useful when you want to insert paper of a different type (or from another source) between every page of your print job. For example, you could use this option to insert blank, colored sheets between overhead transparencies. To enable interleaving pages, select the check box and specify the location from where sheets are to be fed. Also, select the [Duplicate] check box if you want to print the previous page images on the inserted sheet.

## Note

If you enable the Interleave Pages option after enabling the Staple option, the latter will be automatically disabled.

**Paper Type (Insert)** — When you select the MPT option for the paper source of either the Use Front Cover, User Back Cover, Insert Pages, or Interleave Pages option, select the paper type for the paper fed from the MPT.

#### Tip

When both the user management and department management settings are enabled, the quotas that are allowed for the department and user will be displayed in the upper right-hand area of the page.

**Scheduled Print** — Select this option to print a job at a future date and time. When this option is selected, set the date and time to print the job in the [Date & Time] box.

Tips

- Clicking [Print] prints the document, and the print result window is displayed.
- Clicking [Cancel] closes the Print window without printing.
- · Clicking [Reset] restores the default print properties settings.

**6** Click [Close] to return to the [Documents] tab page.

#### Note

When you want to cancel a job before printing is complete, access TopAccess, click the [Job Status] tab > [Print], select the job and press [Delete].

## Selecting test print

This operation allows you to simply print a copy of a document by using the default print properties settings.

- 1 Click the [Documents] tab.
  - The [Documents] tab page is displayed.
- 2 In the Document frame, select the box or folder containing the document that you want to print.



**3** If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].

Password Authentication	
Box Number :	001
Box Name :	User01
Box Password :	
OK Cancel	

#### Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- The password input is displayed in the blank symbols.

Tip

You can also enter the password of a user with an administrator privilege in [Box Password].

# 4 Select the check box of the document that you want to print and select [Test Print] from the [File] menu.

Sectoric Filing				
	File I	Edit	View	Layout
Document	New Folds Open Archive D Upload Ar Test Print Propertie Send Ema	er locument chived D		Doct10510 [Scan]

The Test Print window appears.

## Note

You can also perform test printing by selecting a document in the Document frame and then selecting [Test Print] on the [File] menu. However, you cannot print individual pages, even if you select the check boxes of the pages displayed in the Contents frame.

# **5** Select whether to print all pages of the document or only specified pages and click [Print].

Test Print	
<ul> <li>All Pages</li> <li>1 - 3 Pages</li> </ul>	Department Code :
Print Cancel	

All Pages — Select this option to print all pages of the document.

[first page number] - [last page number] Pages — Select this option to specify the pages to be printed. When this option is selected, enter the numbers of first page and last page to be printed in each box.

**Department Code** — Enter a department code. This must be entered only when the department code is enabled on the equipment.

#### Tips

- When both the user management and department management settings are enabled, the quotas that are allowed for the department and user will be displayed in the upper right-hand area of the page.
- Clicking [Print] prints one copy of the document and the print result window is displayed.
- Clicking [Cancel] closes the Test Print window without printing.

## 6 Click [Close] to return to the [Documents] tab page.

## Note

When you want to cancel a job before printing is complete, access TopAccess, click the [Job Status] tab > [Print], select the job and press [Delete].

## Storing documents

From an application that runs under the Windows operating system, you can send a document as a print job to e-Filing with the printer driver.

You can store your documents in the public box or in a user box.

- P.70 "Saving a print job in the public box"
- P.71 "Saving a print job in a user box"

To use this function, the printing function is required.

## Note

When you store a document in e-Filing by using the printer driver, the printed image (not the original document in your computer) will be stored in e-Filing.

#### Tips

- · For more information about the printer driver, refer to the Printing Guide.
- For a detailed explanation of the public box and user box, see the following page:
   P.6 "e-Filing Features"
- You can also store a scanned document in e-Filing by using the control panel. For details, see the following page:

## □ Saving a print job in the public box

**1** Open the document that you want to store in the box.

Click the [File] menu and select [Print] in your application.

The [Print] dialog box appears.

3 Select the printer driver of the equipment to be used and click [Preferences].


The [Printing Preferences] dialog box appears.

Tip

The procedure for displaying the [Printing Preferences] dialog box for the printer driver may be different depending on the application that you are using. Refer to your application manual about displaying the [Printing Preferences] dialog box.

## ▲ Select the print job type on the [Basic] tab.


- 1) Select [Store to e-Filing] in the [Print Job] box.
- 2) Select other print options as required.
- 3) Click [OK].



5

5

Select [Public Box] to save the print job and click [OK].



Tips

- If you print a job as well as saving it in the public box, select the [Print] check box.
- If you want to save a print job in a specified folder, enter its name in the [Box Folder] box.
   To save data in an existing folder, enter its folder name in the [Box Folder] box.
   To create a new folder and save data in it, enter the new folder name in the [Box Folder] box.

# 6 Click [OK] or [Print] to save the print job.

The print job is saved in the public box.

# Saving a print job in a user box

- Open the document that you want to store in the box.
- Click the [File] menu and select [Print] in your application.

The [Print] dialog box appears.

**3** Select the printer driver of the equipment to be used and click [Preferences]. The [Printing Preferences] dialog box appears.

#### Tip

The procedure for displaying the [Printing Preferences] dialog box for the printer driver may be different depending on the application that you are using. Refer to your application manual about displaying the [Printing Preferences] dialog box.


# ▲ Select the print job type on the [Basic] tab.

- 1) Select [Store to e-Filing] in the [Print Job] box.
- 2) Select other print options as required.
- 3) Click [OK].

Printing Preferences	×
Basic Finishing Paper Handling	Image Quality Effect Others Templates
Print Job:	Original Paper Size: Letter (8 1/2 x 11")
Normal Print	-
Normal Print	Print Paper Size: Image Scale:
Scheduled Print	Same as Original Size 🔻 100 🐥 %(25-400)
Create Print	
Proof Print	Paper Source:
Hold Print	Auto 👻
★₩ Print to Overlay File	Paper Type:
<15 Store to e-Filing	Plain 🔹 🛌
🛛 🕂 Multiple Job Type	Destination
100 %	
Letter	Finisher (Lower)
123 123	A3 A4
Settings	Number of Copies: 1 (1-999)
Profile:	
None	Orientation:
Save Profile Delete	Portrait
	Color:
Restore Defaults	
	Auto    Details
	N
L	
	OK Cancel Help
	° <b>`</b> 5

# **5** Select a user box to save the print job.

- 1) Select the desired user box number from the [Store to] box.
- 2) Enter the password for the user box in the [Password] box.
- 3) If you print a job as well as saving it in the user box, select the [Print] check box.
- 4) Click [OK].



# Tip

If you want to save a print job in a specified folder, enter its name in the [Box Folder] box. To save data in an existing folder, enter its folder name in the [Box Folder] box. To create a new folder and save data in it, enter the new folder name in the [Box Folder] box.

# Note

6

If the Enable SNMP Communication option is enabled on the [Configuration] tab, only the user boxes that have been set up will be displayed in the drop-down list box.

# Click [OK] or [Print] to save the print job.

The print job is saved in the specified user box.

# Archiving documents

The e-Filing web utility allows you to archive the documents stored in e-Filing and download the archived files to your computer. These files can also be uploaded from your computer to e-Filing in the equipment, or other equipment of the same OKI MFP Series.

- P.73 "Downloading an archived document"
- P.76 "Uploading archived documents"

#### Note

The archive files are compatible with the same series of the OKI MFP, not with another series. For example, archived files downloaded from the ES9465 MFP can be uploaded in an OKI MFP in the ES9475 MFP series, not in the ES9455 MFP.

# Downloading an archived document

You can archive the documents in the box and download it to your computer. Use this feature to create a back-up file of your documents in e-Filing.


The following procedure describes an example of how to download an archived document when using Microsoft Internet Explorer.

### Notes

- The archived file contains all the documents you have specified to the archive, but you cannot open the documents on your computer.
- You can create an archived file that contains multiple documents in the same folder or the same box.
- You cannot create an archived file that contains more than 2 GB of data.
- Do not close the main window and child window by clicking [X]. If you do, downloading the archived documents becomes impossible. If you close the window by clicking [X] by mistake, turn the power to the equipment off and then on again.

# 1 Click the [Documents] tab.

- The [Documents] tab page is displayed.
- 2 In the Document frame, select the box or folder containing the document that you want to archive.



**3** If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].


Password Authentication	
Box Number :	001
Box Name :	User01
Box Password :	
OK N Cancel	

#### Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- The password input is displayed in the blank symbols.

You can also enter the password of a user with an administrator privilege in [Box Password].

# **4** Select the check box of the document that you want to archive and select [Archive Document] from the [File] menu.



The confirmation dialog box appears.

### Note

Users can also archive a document by selecting the document in the Document frame, clicking on the [File] menu and selecting [Archive Document]. However, you cannot archive individual pages, even if you select the check boxes of the pages displayed in the Contents frame.

# **5** Click [OK] to start archiving the document.

Message fr	om webpage 🛛 🔀
?	Do you want to archive the document? This process may take some time.
	OK Cancel

Tip

6 The Archive Document window appears. During archiving, you can quit the process by clicking [Cancel].

Archive Document
This process may take some time.
This process may take some time. Please wait while the document is compressed and a downloadable archive file is created.
65 %
Cancel

When archiving the document has been completed, "Your document has been archived successfully" is displayed.

#### Note

Do not perform any operation while the e-Filing web utility is running busy.



Click the file name link to download the archived file.

Archive Do	cument
Your docume	nt has been archived successfully.
You can now The link will I File Name :	05:10:2011 09:40:42
Close	

The [File Download] dialog box appears.

8	Click	[Save]
---	-------	--------

File Downl	oad
Do you	want to open or save this file?
1	Name: 20110510_15442.zip
10	Type: Compressed (zipped) Folder, 21.9MB
	From: 157.69.73.250
🔽 Al <u>w</u> ay	<u>Open</u> <u>Save</u> Cancel s ask before opening this type of file
	While files from the Internet can be useful, some files can potentially harm your computer. If you do not trust the source, do not open or save this file. <u>What's the risk?</u>

The [Save As] dialog box appears.



Locate the folder where you want the archived file saved and click [Save].

Organize 🔻 New fold	der	u= • 6
Favorites Desktop	Libraries System Folder	
🖳 Recent Places	User001 System Folder	
🕞 Libraries	Computer System Folder	
📬 Network	Network System Folder	
	Drivers File folder	
File name: 2011	.0510_15442	
Save as type: Com	npressed (zipped) Folder	

This starts downloading the file.

# 10 Click [Close].

rour documer	it has been archived successfully.
Please click th	ie link below.
	fownload the archived file onto your system.
	unch a file download dialog allowing you to select a name and path for the zip file.
	20110510_15442.zip
Created :	05:10:2011 09:40:42
Size (KB) :	21 MB
Close	

# **Uploading archived documents**

If you have an archived file that has been downloaded from the equipment to your computer, you can upload it to e-Filing. When you upload the archived file, the file is automatically extracted and documents will be created in the box specified.

# Notes

- If the same name document already exists in the box, the extracted document will be renamed by adding a 3-digit number to the original name.
- Do not close the main window and child window by clicking [X]. If you do, uploading the archived documents becomes impossible. If you close the window by clicking [X] by mistake, turn the power to the equipment off and then on again.
- 1 Click the [Documents] tab.

The [Documents] tab page is displayed.

**2** In the Document frame, select the box or folder where you want to upload the archived documents.



**3** If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].

Password Authentication	
Box Number :	002
Box Name :	User02
Box Password :	
OK Cancel	


Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- · The password input is displayed in the blank symbols.

Tip

You can also enter the password of a user with an administrator privilege in [Box Password].

**4** Select [Upload Archived Document] from the [File] menu.



The Upload Archived Document window appears.

"

Click [Browse].		
Upload Archived Document		
Archived File :	Browse	

The [Choose File] dialog box appears.



# Select the archived file to be uploaded and click [Open].

Choose File to Upload						×
G v Archive >		• <sup>4</sup> j	Search Arch	ive		ρ
Organize 🔻 New folder				1.	•	0
Computer Computer	20110510_15442 Compressed (zipped) Folder		1			
File <u>n</u> ame:	20110510_15442	•	All Files (*.*) <u>O</u> pen	\ \\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\	Cancel	•


This will return you to the Upload Archived Document window, and the folder path of the selected file will be displayed in the [Archived File] box.

# 7 Click [OK].

Archived File : C:\Users\User001\Desktop\Archive\2 Browse	
Cancel	

The confirmation dialog box appears.

8 Click [OK] to start uploading the archived file.



## Note

If you select an archived file unsupported in your model or a file other than an archived one, an error message appears. In that case, select the correct archived file and try again.

# **9** The Upload Archive Document window shows the process of uploading. During the uploading process, you can quit uploading by clicking [Cancel].

Upload Archived Document		
This process may take some time.		
Please wait while the archived file is uploaded to the selected box.		
25 %		

When uploading the archived file has been completed, "Your document has been uploaded successfully" is displayed.

# Note

Do not perform any operation while the e-Filing web utility is running busy.

# 10 Click [Close].

Upload Archived Document	
Your document has been uploaded succe	ssfully.
Close	
42	

The documents are added to the selected box.

# Sending Email

You can send the selected documents as Emails from the e-Filing web utility. When you perform this function, the equipment creates an Email with the selected documents as an attached file and sends the Email directly from the equipment.

To use this function, the scanning function is required.

### Notes

- To use the Send Email function, the Email configuration of the equipment needs to be set by the network administrator.
- When using a multifunctional digital color system (color MFP), you can send e-Filing documents as Emails only when they have been saved under the conditions noted below. Check the document properties before sending the documents.
  - Documents which were saved with the copy function of the equipment in the black TEXT/PHOTO or black -TEXT mode
  - Documents which were saved with the scanning function of the equipment
  - Documents which were saved with the received fax/Internet Fax transferred function

- 1 Click the [Documents] tab.
- The [Documents] tab page is displayed.
- 2 In the Document frame, select the box or folder containing the document that you want to send as an Email.



**3** If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].

Password Authentication	
Box Number :	001
Box Name :	User01
Box Password :	
OK Cancel	


#### Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- · The password input is displayed in the blank symbols.

Tip

You can also enter the password of a user with an administrator privilege in [Box Password].

# 4 Select the check box of the document that you want to send as an Email and select [Send Email] from the [File] menu.



The Send Email page is displayed.

Tips

- Users can also send a document as an Email by selecting the document in the Document frame, clicking on the [File] menu and selecting [Send Email].
- Users can also send up to 100 individual pages or documents by selecting the check boxes displayed in the Contents frame.

5 Specify the following items as required and click [Send].

TO: Destination Setting	
TO: Destination single	
CC: Destination Setting	
CC: Destination	
BCC: Destination Setting	
BCC: Destination	
Email Setting	
Required	
Subject	Send data from (Device name) (Box Info.)
Subject	Add the date and time to the subject
*From Address	User01@example.com
From Name	User01
Body File Format	▼ PDF(Multi) ▼
rile Format	
	Encryption
	User Password Master Password
Encryption	Encryption Level 128-bit AES  Authority
Encryption	Authority
Encryption	Authority  Printing  Change of Documents  Content Copying or Extraction
	Authority

**[TO: Destination Setting]** — Click this button to specify the destination. When you click this button, the Recipient List page appears. For instructions on how to specify the destination, see the following section:

[CC: Destination Setting] - Click this button to specify the CC destination.

[BCC: Destination Setting] — Click this button to specify the BCC destination.

**Subject** — This option sets the subject of the Email documents. Select [Send data from (Device name) (Box Info.)] set by default, or enter the desired subject in the box. When you want to add the date and time to the subject, select the [Add the date and time to the subject] check box.

**From Address** — Enter the Email address of the sender. When the recipient replies, the message will be sent to this Email address.

From Name — Enter the sender's name of the Email document.

**Body** — Enter the body message of the Email document. You can enter up to 1000 characters (including spaces). **File Format** — Select the file format to which the received document will be converted.

- TIFF (Multi) Select this option to save the scanned images as a multi-page TIFF file.
- TIFF (Single) Select this option to save the scanned images separately as single-page TIFF files.
- PDF (Multi) Select this option to save the scanned images as a multi-page PDF file.
- PDF (Single) Select this option to save the scanned images separately as single-page PDF files.
- XPS (Multi) Select this option to save the scanned images as a multi-page XPS file.
- XPS (Single) Select this option to save the scanned images separately as single-page XPS files.
- JPEG Select this option to save the scanned images as JPEG files. This option is selectable only when you have scanned the images with either [FULL COLOR] or [GRAY SCALE].

# Notes

- If the forced encryption setting is enabled, only [PDF (Multi)] and [PDF (Single)] are selectable for the file format. For the forced encryption function, refer to the *MFP Management Guide*.
- Files saved in the XPS format can be used in Windows Vista, Windows 7, and Windows Server 2008, or Windows XP SP2, Windows Server 2003 SP2 or later versions with Net Framework 3.0 installed.

**Encryption** — Set this option for encrypting PDF files if you have selected [PDF (Multi)] or [PDF (Single)] as the file format setting.

- Encryption Select this check box if you want to encrypt PDF files.
- User Password Enter a password for opening encrypted PDF files.

• Master Password — Enter a password for changing the encryption PDF setting.

#### Tips

- If the forced encryption setting is enabled, you cannot clear the [Encryption] check box. For the forced
  encryption function, refer to the *MFP Management Guide*.
- The user password and the master password are not set at the factory shipment. If the master password is to be set, ask your network administrator.
- A password must be entered in one-byte alphanumeric characters. The minimum and maximum numbers of characters allowed are 1 and 32.
- The user password must differ from the master password.

## Notes

- These passwords can be re-entered only by an authorized user. Users cannot change the settings of the [Encryption Level] box and the [Authority] box noted below if they are not authorized to change the master password. Ask the administrator about resetting these passwords.
- For details of the encryption setting, refer to the MFP Management Guide.
- **Encryption Level** Select the desired encryption level.
- **40-bit RC4** Select this option to set an encryption level to the one compatible with Acrobat 3.0, PDF V1.1.
- 128-bit RC4 Select this option to set an encryption level to the one compatible with Acrobat 5.0, PDF V1.4.
- **128-bit AES** Select this option to set an encryption level to the one compatible with Acrobat 7.0, PDF V1.6.
- Authority Select the check box of the desired type for the encrypt PDF authority.
  - Printing
  - Change of Documents
  - Content Copying or Extraction
  - Content Extraction for accessibility

File Name — Select how the attached file will be named. Select [DocYYMMDD] to name it as described, select [Original Document Name] to use the original document name, or you can enter the desired file name in the field. Fragment Message Size — Select the size of the message fragmentation. Department Code — Enter the department code if required.

# 6 Click [Close].

Electr	onic Filing		
Send Email			
Your document h	as been sent successfu	illy.	
Close			

# Destination setting

On the Recipient List page, you can specify up to 400 destinations to send e-Filing documents as Email. You can specify the recipients by entering the Email addresses manually, selecting the recipients from an address book, selecting the recipient groups from an address book, or searching the LDAP server for recipients.

## Note

If [LDAP Authentication] is selected in [Authentication Type], you can choose only destinations that are registered in the authenticated LDAP servers. For details of the LDAP Authentication option, refer to the *TopAccess Guide*.

- P.82 "Entering recipients manually"
- P.83 "Selecting recipients from an address book"
- P.84 "Selecting groups from an address book"
- P.85 "Searching the LDAP server for recipients"
- P.86 "Removing contacts from the recipient list"

# **Entering recipients manually**

Follow the steps below to manually add a recipient to the Recipient List.

# Click [Destination Setting] to open the Recipient List page.

2 Click [New].

Recipient List		
Save Cancel New	Address Book Address Group Sean	Delete
<u>⊾</u> <u>Name</u> 1	Destination	

The Contact Property page is displayed.



Contact Property	
OK Cancel Reset	
*Destination User002@example.com	
₩1	

The entered recipient is added to the Recipient List page.

# ▲ Repeat steps 2 and 3 to add all the recipients as required.

Tip

You can remove contacts once added to the recipient list before saving the destination settings. P.86 "Removing contacts from the recipient list"

# Click [Save].

5

Recipient List	Recipient List				
Save Cancel New	Address Book Address Group Search Delete				
⊻ <mark>√N</mark> ame	Destination				
	User002@example.com				

The contacts are added as the destinations.

# Selecting recipients from an address book

Follow the steps below to select recipients from an address book.

- Click [Destination Setting] to open the Recipient List page.
- 2 Click [Address Book].

Recipient List				
Save Cancel New	Address Book	Address Group	Search Delete	
<u>▼Name</u>	Destination			

The Address Book page is displayed.

# 3 Select the Email check boxes of the users you want to add and click [Add].

	ess Book All Groups 🔹 Cancel	
Email	<b>▼</b> Name	Email Address
	User010	User010@example.com
	User009	User009@example.com
	User008	User008@example.com
	User007	User007@example.com
	User006	User006@example.com
	User005	User005@example.com
	User004	User004@example.com
	User003	User003@example.com
	User002	User002@example.com
	User001	User001@example.com
A	of this page	

The selected recipients are added to the Recipient List page.

#### Tips

- If you want to sort recipients into specific groups, select the desired group name in the [Group] box.
- You can remove contacts once added to the recipient list before saving the destination settings.
   P.86 "Removing contacts from the recipient list"

# 4 Click [Save].

Re	cipient List	
Sa	ve Cancel New Add	ress Book Address Group Search Delete
~	Vame	Destination
	User004	User004@example.com
	User003	User003@example.com
	User002	User002@example.com

The contacts are added as the destinations.

# Selecting groups from an address book

Follow the steps below to select groups from an address book.

- **1** Click [Destination Setting] to open the Recipient List page.
- 2 Click [Address Group].

Recipient List		
Save Cancel New	Address Book	Address Group Search Delete
<u>▼Name</u>	Destination	5

The Address Group page is displayed.

**3** Select the group check boxes containing the desired recipients and click [Add].

Add	ress Group	
Add	Cancel A	
	6	
Group	▼ <u>Group Name</u>	
	Group03	
	Proup02	
	Group01	
	p of this page	1

All recipients in the selected groups are added to the Recipient List page.

## Tip

You can remove contacts once added to the recipient list before saving the destination settings.  $\square$  P.86 "Removing contacts from the recipient list"

# **4** Click [Save].

Save Cancel New Address Book Address Group Search Delete	Recipient List	
	Save Cancel New	Address Book Address Group Search Delete
	⊻ <mark>Name</mark>	Destination
Group01 Group	Group01	Group

The contacts are added as the destinations.

# Searching the LDAP server for recipients

Follow the steps below to search the registered LDAP server for recipients.

#### Tip

To search the LDAP server for recipients, an administrator must set up the directory service by using TopAccess in the administrator mode. For details, refer to the **TopAccess Guide**.

### Click [Destination Setting] to open the Recipient List page.

# Click [Search].

Recipient List				
Save Cancel New	Address Book	Address Group	Search Delete	
▶ Name	Destination		43	

The Search Contact page is displayed.

# **3** Specify the search condition.

- 1) Select the directory service name that you want to search in the [Directory Service Name] box.
- 2) Enter the search terms in the fields that you want to search.
- 3) Click [Search].

Search Cancel Inter a Contact. Directory Service Name LDAP01 First Name Last Name User Email Address Fax Number Fax Number				
Directory Service Name LDAP01				
Directory Service Name LDAP01				
First Name User Email Address				
Last Name User Email Address				
Email Address				
Fax Number				
Company				
Department				
	- ht	-		
	· v	L		

TopAccess will start searching the LDAP server for recipients, and the Search Address List page will display the results.

#### Tips

- If you select the model name of the equipment in the [Directory Service Name] box, you can search the
  address book of the equipment for recipients.
- TopAccess will search for the recipients that match the entries.
- Fill in at least one of the fields to perform a wild-card search.

**A** Select the Email check boxes of the users you want to add and click [Add].

Se	ar	ch Address List			
Ad		Cancel			
V		<u>Vame</u>	company	department	Email Address
	Ust	010			User010@example.com
	Use	009			User009@example.com
	Use	008			User008@example.com
	Use	007			User007@example.com
	Use	006			User006@example.com
0	Use	005			User005@example.com
V	Use	004			User004@example.com
V	Use	003			User003@example.com
V	Use	002			User002@example.com
	t	001			User001@example.com

The selected recipients are added to the Recipient List page.

#### Tip

You can remove contacts once added to the recipient list before saving the destination settings. P.86 "Removing contacts from the recipient list"

# 5 Click [Save].

Recipient List	ress Book Address Group Search Delete
⊻ <mark>N</mark> iame	Destination
User004	User004@example.com
User003	User003@example.com
User002	User002@example.com
· · · ·	

The contacts are added as the destinations.

# Removing contacts from the recipient list

1 Select the check boxes of the contacts that you want to remove from the recipient list, and click [Delete].

Sa	ve	Cancel New Add	Iress Book Address Group Search Delete
~		ame	Destination
V	Use	004	User004@example.com
1	Use	003	User003@example.com
$\checkmark$	Use	002	User002@example.com

The selected contacts are removed from the recipient list.

# 6

# **EDITING DOCUMENTS**

This chapter provides instructions on how to edit documents by using the e-Filing web utility.

About the Document Control Buttons	
Editing With Pages in Your Documents	
Displaying document and page properties	
Copying pages from one document to another	
Copying pages from a document to a box or folder	
Deleting pages from a document	
Inserting a blank page into a document	
Moving pages within a document	104
Moving and Merging Documents	
Moving documents	
Merging documents	

# **About the Document Control Buttons**

The e-Filing web utility allows you to make changes to your stored documents before you print them. Three document control buttons are provided in the e-Filing web utility: [Edit], [Save], and [Cancel]. These buttons are displayed at the top of the Contents frame when you select a document in the Document frame. The buttons displayed vary depending on the document status.

- **[Edit]** Click this button to start editing the document. Only this button is displayed when you are in the View mode, where the document status indicates "View". When you click [Edit], the document status will be changed to "Editing", [Save] and [Cancel] appear instead of [Edit], and you can edit the document. If you click this button when the document status indicates "In Use", you cannot enter the Edit mode and the message "The Document is being used. Please try again later" is displayed.
- [Save] Click this button to save the document that you have edited. This button is displayed only when you are in the Edit mode, where the document status indicates "Editing". When you click this button, the document is saved and returns to the View mode.
- **[Cancel]** Click this button to return to the View mode without saving the document. This button is displayed only when you are in the Edit mode, where the document status indicates "Editing".

The document status is displayed to the left of these buttons. The document status indicates the following situations:

- In Use This indicates that another user is currently editing the document.
- View This indicates that the document is currently in the View mode, and you can only view the pages within the document.
- Editing This indicates that the document is currently in the Edit mode, and you can edit the document.

# Note

When you edit or delete a document that is shared by other users, make sure to refresh the display to see the latest status of the document. If the two or more users try to edit or delete the document or the page at the same time, the data may be damaged.

# **Editing With Pages in Your Documents**

The e-Filing web utility allows you to copy, move, delete and insert pages and change the order of pages in your document.

P.89 "Displaying document and page properties"

P.90 "Copying pages from one document to another"

P.95 "Copying pages from a document to a box or folder"

P.99 "Deleting pages from a document"

P.101 "Inserting a blank page into a document"

P.104 "Moving pages within a document"

# Displaying document and page properties

You can display the Document Properties and Page Properties windows that contain details of the document or page. To display the Document Properties window, select the check box of the document and select [Properties] from the [File] menu. To display the Page Properties window, select the check box of the page and select [Page Properties] from the [File] menu.

The Document Properties window contains the following information:

Location :	e-Filing/User01/	
Total Page(s) :	3	
Size :	19 MB	
Created :	2011.05.10 09:05:09	
Modified :	2011.05.10 09:05:11	
Last Accessed :	2011.05.10 10:00:59	

Location

Displays the directory where the document is located.

- Total Page(s)
  - Displays the number of pages the document contains.
- Size
- Displays the data size of the document.
- · Created

Displays the date and time the document was created.

Modified

Displays the date and time the document was last modified.

- Last Accessed
- Displays the date and time the document was last accessed by any user.
- [OK]

Click this button to close the window.

The Page Properties window contains the following information:

Page Properties		
	DOC110510-001 (1/3)	
Format:	Сору	
Resolution:	600 x 600	
Image Size :	4867 × 6922	
Paper Size :	A4	
Size :	6710 KB	
OK		

Format

Displays how the page is stored. Resolution


- Displays the resolution of the page.
- Image Size Displays the pixel size of the page.

- Paper Size
- Displays the paper size of the page. • Size
- Displays the data size of the page.
- [OK] Click this button to close the window.

# Copying pages from one document to another

You can copy or cut pages from a document and insert them into another one.

- 1 Click the [Documents] tab.
- The [Documents] tab page is displayed.
- **2** In the Document frame, select the box or folder containing the document whose pages you want to copy or cut.



**3** If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].

Password Authentication	
Box Number :	001
Box Name :	User01
Box Password :	
OK Cancel	


# Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- The password input is displayed in the blank symbols.



You can also enter the password of a user with an administrator privilege in [Box Password].

▲ In the Document frame, select the document whose pages you want to copy or cut.



The pages of the document are displayed in the Contents frame.


#### Tip

If you want to cut pages from the document, click [Edit] to enter the Edit mode. Clicking [Edit] changes the document status from the View mode to the Edit mode so that you can cut pages from the document.

#### Note

If the document status indicates "In Use", you cannot enter the Edit mode because another user is currently editing the document.

# 5 Select the check boxes of the pages that you want to copy or cut, and select [Copy] or [Cut] from the [Edit] menu.




- When you have cut pages from the document, proceed to the next step after the process is completed.
- When you have copied pages from the document, proceed to step 8 after the process is completed.

### Note

Do not perform any operation while the e-Filing web utility is busy.

6 Click [Save] to save the document.



The Save Document window appears.

7 Enter the document name in the [Document Name] box and click [Save].




- If you rename the document, it will be saved as a new one. If you do not change the document name, the original document will be overwritten.
- The Contents frame displays the pages in the View mode.
- The document status is returned to the View mode from the Edit mode.

# Note

Do not close the Save Document window by clicking [X]. The operations may no longer work properly. If you close the window by clicking [X] by mistake, turn the power to the equipment off and then on again.

# 8 In the Document frame, select the box or folder containing the document into which you want to insert the copied pages.



**9** If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].

Password Authentication	
Box Number :	002
Box Name :	User02
Box Password :	
OK Cancel	


## Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- · The password input is displayed in the blank symbols.

Tip

You can also enter the password of a user with an administrator privilege in [Box Password].

# **10** In the Document frame, select the document into which you want to insert the copied pages, and click [Edit].



The pages of the document are displayed in the Contents frame, and the document status is changed to the Edit mode from the View mode.


#### Note

If the document status indicates "In Use", you cannot enter the Edit mode because another user is currently editing the document.

## **11** Click the space between the pages where you want to insert the copied pages.


Electronic Filing	g							Do	ocuments	Preferences	<u>Login</u>
	File	Edit	View	Layout	E	i 🖪 🎒 X	њ (2).	< <	> >		
Document	RD	OC110510-0	002 (1/3)					Status	: Editing	Save	ancel
			Jes 1		A starting and a start and a s		CONTENTS The second se		~		
<ul> <li>■ 005 User05</li> <li>■ 1005 User05</li> <li>■ 1006 User06</li> <li>■ 1007 User07</li> </ul>											
Cline.											

The arrow indicators move to the space between the pages where you clicked.




The copied pages are inserted between the specified pages.

1	3	Click	[Save].
---	---	-------	---------



The Save Document window appears.

# **1 L** Enter the document name in the [Document Name] box and click [Save].



- If you rename the document, it will be saved as a new one. If you do not change the name, the original document will be overwritten.
- The document status is returned to the View mode from the Edit mode.




Do not close the Save Document window by clicking [X]. The operations may no longer work properly. If you close the window by clicking [X] by mistake, turn the power to the equipment off and then on again.

# Copying pages from a document to a box or folder

You can copy or cut pages from a document and save them in a box or folder as a new document.

- 1 Click the [Documents] tab.
  - The [Documents] tab page is displayed.
- 2 In the Document frame, select the box or folder containing the document whose pages you want to copy or cut.



**3** If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].


Password Authentication	
Box Number :	001
Box Name :	User01
Box Password :	
OK Cancel	

### Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- The password input is displayed in the blank symbols.

#### Tip

You can also enter the password of a user with an administrator privilege in [Box Password].



▲ In the Document frame, select the document whose pages you want to copy or cut.

The pages of the document are displayed in the Contents frame.


#### Tip

If you want to cut pages from the document, click [Edit] to enter the Edit mode. Clicking [Edit] changes the document status from the View mode to the Edit mode so that you can cut pages from the document.

#### Note

If the document status indicates "In Use", you cannot enter the Edit mode because another user is currently editing the document.

# 5 Select the check boxes of the pages that you want to copy or cut, and select [Copy] or [Cut] from the [Edit] menu.




- When you have cut pages from the document, proceed to the next step after the process is completed.
- When you have copied pages from the document, proceed to step 8 after the process is completed.

# Note

Do not perform any operation while the e-Filing web utility is running busy.

Click [Save] to save the document.

6



The Save Document window appears.

# **7** Enter the document name in the [Document Name] box and click [Save].


Save
Document Name DOC110510-001
Save Cancel

- If you rename the document, it will be saved as a new one. If you do not change the name, the original document will be overwritten.
- · The document status is returned to the View mode from the Edit mode

### Note

Do not close the Save Document window by clicking [X]. The operations may no longer work properly. If you close the window by clicking [X] by mistake, turn the power to the equipment off and then on again.

# 8 In the Document frame, select the box or folder where you want to store the copied pages.



**9** If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].

Password Authentication	
Box Number :	002
Box Name :	User02
Box Password :	
OK Cancel	


## Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- · The password input is displayed in the blank symbols.

Tip

You can also enter the password of a user with an administrator privilege in [Box Password].

**10** Click the [Edit] menu and select [Paste].



The document containing the copied pages is created in the selected box or folder.

# Deleting pages from a document

You can delete pages from a document.

**1** Click the [Documents] tab.

The [Documents] tab page is displayed.

2 In the Document frame, select the box or folder containing the document whose pages you want to delete.

C Electronic Filin	ng				
	File	Edit	View	Layout	
Document	増 e-F	Filing (8 it	ems)		
				â	
		Public B	х	🔲 001 User0	1

**3** If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].

Password Authentication	
Box Number :	001
Box Name :	User01
Box Password :	
OK Cancel	

#### Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- · The password input is displayed in the blank symbols.

#### Tip

You can also enter the password of a user with an administrator privilege in [Box Password].

# In the Document frame, select the document whose pages you want to delete, and click [Edit].


🝞 Electronic Filing	g			Docu	iments Preferen	ces <u>Logi</u> r
	File Edit	View Layout	₹ - 4	)X∎®. K<>	· >	
Document	DOC110510-00 Quick Start Guide			and a second sec	Status : View	Edit

The pages of the document are displayed in the Contents frame, and the document status is changed to the Edit mode from the View mode.

# Note

If the document status indicates "In Use", you cannot enter the Edit mode because another user is currently editing the document.

**5** Select the check boxes of the pages that you want to delete and select [Delete] from the [Edit] menu.



The confirmation dialog box appears.



Message fr	om webpage Do you want to delete t	he page(s)?
	ОК	Cancel

The selected pages are deleted.

# 7 Click [Save] to save the document.



The Save Document window appears.



Enter the document name in the [Document Name] box and click [Save].

Save Document Name DOC110510-001	
Save Cancel	

- If you rename the document, it will be saved as a new one. If you do not change the name, the original document will be overwritten.
- · The document status is returned to the View mode from the Edit mode.

# Note

Do not close the Save Document window by clicking [X]. The operations may no longer work properly. If you close the window by clicking [X] by mistake, turn the power to the equipment off and then on again.

# Inserting a blank page into a document

You can insert a blank page into a document. You can select a different size for the blank pages.

1 Click the [Documents] tab.

The [Documents] tab page is displayed.

**2** In the Document frame, select the box or folder containing the document into which you want to insert a blank page.

Sectronic Filing	g				
	File	Edit	View	Layout	
Document	/ 🗐 e-F	iling (8 ite	ems)		
		Î			
🖲 🗑 007 User07		Public Bo	×	001 User01	

**3** If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].

Password Authentication	
Box Number :	001
Box Name :	User01
Box Password :	
OK Cancel	


# Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- · The password input is displayed in the blank symbols.

# Tip

You can also enter the password of a user with an administrator privilege in [Box Password].

# **4** In the Document frame, select the document into which you want to insert a blank page, and click [Edit].




The pages of the document are displayed in the Contents frame, and the document status is changed to the Edit mode from the View mode.

# Note

If the document status indicates "In Use", you cannot enter the Edit mode because another user is currently editing the document.


6



Click the space between the pages where you want to insert a blank page. 5

The arrow indicators move to the space between the pages where you have clicked.

# Click the [Layout] menu and select [Insert Blank Page].



The Insert Blank Page window appears.


#### Select the paper size and orientation of the inserted blank page, and click [OK]. 7

Insert Blank Page			
Select the paper size for the blank she	et to insert.		
Letter (8.5 x 11 in)	Portrait		
Legal (8.5 x 14 in)	C Landscape		
A4 (210 x 297 mm)			
Statement (5.5 x 8.5 in)			
A3 (297 x 420 mm)			
B4 (257 x 364 mm)			
B5 (182 x 257 mm)			
Ledger (11 x 17 in)			
Computer (10 1/8 x 14 in)			
Folio (210 x 330 mm)			
A5 (148 x 210 mm)			
A6 (105 x 148 mm)			
13"LG (8.5 x 13 in)			
8.5"SQ (8.5 x 8.5 in)			
8K (270 x 390 mm)			
16K (270 x 195 mm)			
A3-WIDE (305 x 457 mm)			
(12 x 18 in)			
320 x 450			
320 x 460			
(13 x 19 in)			
OK Cancel			
$\sim$			

A blank page is inserted between the specified pages.



Its available size differs depending on the model.



The Save Document window appears.

# Enter the document name in the [Document Name] box and click [Save].

Save
Document Name DOC110510-001
Save Cancel

- If you rename the document, it will be saved as a new one. If you do not change the name, the original document will be overwritten.
- The document status is returned to the View mode from the Edit mode.

# Note

9

Do not close the Save Document window by clicking [X]. The operations may no longer work properly. If you close the window by clicking [X] by mistake, turn the power to the equipment off and then on again.

# Moving pages within a document

You can move pages within a document to rearrange the page order.

- 1 Click the [Documents] tab.
  - The [Documents] tab page is displayed.
- 2 In the Document frame, select the box or folder containing the document whose pages you want to rearrange.

C Electronic Filin	g				
	File	Edit	View	Layout	
Document	僧 e-F	iling (8 it	ems)		
		Î		â	
		Public Bo	X	🔲 001 User01	

**3** If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].

Password Authentication	
Box Number :	001
Box Name :	User01
Box Password :	
OK Cancel	

### Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- · The password input is displayed in the blank symbols.

### Tip

You can also enter the password of a user with an administrator privilege in [Box Password].

# **4** In the Document frame, select the document whose pages you want to rearrange, and click [Edit].

Selectronic Filin	g				Documents Preferences	ogin
	File Edit	View	Layout	5 - <i>8</i> / 6 / 6	< < > >	
Document	B DOC110510-	001 (1/3)			Status : View Edit	
	Quick Start Guide		Image: Strategy of the	Pages 3	Å	2


The pages of the document are displayed in the Contents frame, and the document status is changed to the Edit mode from the View mode.

### Note

If the document status indicates "In Use", you cannot enter the Edit mode because another user is currently editing the document.

6

5 Select the check boxes of the pages that you want to move between other pages and select [Cut] from the [Edit] menu.




The selected pages are copied to the clipboard and deleted from the document.

#### Note

Do not perform any operation while the e-Filing web utility is running busy.




Click the space between the pages where you want to insert the copied pages.




The arrow indicators move to the space between the pages where you have clicked.

# 7 Click the [Edit] menu and select [Paste].



The copied pages are inserted between the specified pages.

**8** Continue the procedure from steps 5 to 7 to rearrange the pages.



**9** After you have completed rearranging the pages, click [Save].

The Save Document window appears.

# **10** Enter the document name in the [Document Name] box and click [Save].

Save
Document Name DOC110510-001
Save Cancel

- If you rename the document, it will be saved as a new one. If you do not change the name, the original document will be overwritten.
- The document status is returned to the View mode from the Edit mode.

# Note

Do not close the Save Document window by clicking [X]. The operations may no longer work properly. If you close the window by clicking [X] by mistake, turn the power to the equipment off and then on again.

# **Moving and Merging Documents**

You can move documents between boxes or folders. You can also combine several documents into one document.

P.109 "Merging documents"

### Moving documents

You can move a document from one box or folder to another, to help you manage the documents.

- **1** Click the [Documents] tab.
- The [Documents] tab page is displayed.
- **2** In the Document frame, select the box or folder containing the document that you want to move.

**3** If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].


Password Authentication	
Box Number :	001
Box Name :	User01
Box Password :	
OK Cancel	

### Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- · The password input is displayed in the blank symbols.

Tip

4 Select the check boxes of the documents that you want to move and select [Cut] from the [Edit] menu.



The selected documents are copied on the clipboard and deleted from the current box or folder.

### Note

Do not perform any operation while the e-Filing web utility is running busy.

**5** In the Document frame, select the box or folder where you want to paste the documents.

Sectronic Filin	g					Documents	Preferences	<u>Login</u>
	File	Edit	View	Layout	5 I 4 % h C	< < > >		
Document	🔠 Use	er01 (2 iter	ns)					
		Folder01		Corrections of the correction				

6 If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].


Password Authentication	
Box Number :	002
Box Name :	User02
Box Password :	
OK Cancel	

### Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- · The password input is displayed in the blank symbols.

### Tip

# 7 Click the [Edit] menu and select [Paste].



The documents are created in the selected box or folder.

### Merging documents


You can copy an entire document and insert its pages into another document. The document that you want to insert is the source document, and the document that you want to merge it into is the destination document.



### Click the [Documents] tab.

The [Documents] tab page is displayed.

# **2** In the Document frame, select the box or folder containing the source documents.



**3** If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].


Password Authentication	
Box Number :	001
Box Name :	User01
Box Password :	
OK Cancel	

### Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- The password input is displayed in the blank symbols.

### Tip

4 Select the check boxes of the source documents and select [Copy] from the [Edit] menu.




The selected documents are copied to the clipboard.

### Note

Do not perform any operation while the e-Filing web utility is busy.



In the Document frame, select the box or folder containing the destination document.



6 If you select a box that is protected with a password, the Password Authentication window appears. Enter the password in the [Box Password] box and click [OK].


Password Authentication	
Box Number :	002
Box Name :	User02
Box Password :	•••••
OK Cancel	

### Notes

- If you enter an invalid password several times to open the box, you may not log in for a certain period since it will be regarded as an unauthorized access. When "Box is locked." appears and logging in cannot be performed, ask your administrator.
- · The password input is displayed in the blank symbols.

### Tip

**7** In the Document frame, select the destination document, and click [Edit].




The pages of the document are displayed in the Contents frame, and the document status is changed to the Edit mode from the View mode.

### Note


If the document status indicates "In Use", you cannot enter the Edit mode because another user is currently editing the document.

### **8** Click the space between the pages where you want to merge the documents.



The arrow indicators move to the space between the pages where you have clicked.

### Click the [Edit] menu and select [Paste].



The copied documents are merged between the specified pages.


### Tip

9

If multiple documents have been copied, the documents are merged in order from the oldest one.


6

# 10 Click [Save].



The Save Document window appears.

# **11** Enter the document name in the [Document Name] box and click [Save].



- If you rename the document, it will be saved as a new one. If you do not change the name, the original document will be overwritten.
- The document status is returned to the View mode from the Edit mode.

### Note

Do not close the Save Document window by clicking [X]. The operations may no longer work properly. If you close the window by clicking [X], turn the power to the equipment off and then on again.

# 

# SYSTEM ADMINISTRATION

This chapter describes system administration of the e-Filing features.

Safeguarding Data	114
Erasing boxes	
Unlocking user boxes	. 115

# **Safeguarding Data**

An administrator should periodically monitor e-Filing to make sure it has enough hard disk space for everyday operations. This section describes the administrator's function that allows you to delete boxes and the unlocking method of the user boxes which have been locked by incorrect password entries.

```
P.114 "Erasing boxes"
```

P.115 "Unlocking user boxes"

# Erasing boxes

You can manually erase boxes in e-Filing if the data has been corrupted, for example, by a hard disk failure and is therefore no longer usable.

### **1** Log on to the Administrator page.

P.37 "Logging in as a system administrator" The Box Management page is displayed.

### Notes

- It is recommended to archive the documents in the boxes before deleting them. Once the boxes have been deleted, you cannot restore the documents in the boxes.
- P.73 "Archiving documents"
- The Backup/Restore utility included in the Client Utilities CD-ROM allows you to back up data in the boxes.

### Tip

You can display the Box Properties window by clicking the box number or box name link.

### **2** Select the check boxes of the user boxes that you want to delete and click [Delete].

Filing Disk Sp	ace Available : 10142 MB					
	Stored Data	Data Type	Data Size		Remark	ks
	Box	Shared File	97 MB			
Delete Unio	ck					
at 1 🔪	<ul> <li>Development or</li> </ul>	Day Name		Head as	a neitre	Ctatura
1 VZ	Box Number	Box Name		Used ca 57 M		Status
νZ	001	User01		Used ca 57 M 5 Ki	8	<u>Status</u>
2 VZ	▲ Box Number 001 002 003			57 N	8	<u>Status</u>
יע <b>צ</b> יי יי	001	User01 User02		57 M 5 Ki	B 9	<u>Status</u>
2 2 2 2	001 002 003	User01 User02 User03		57 M 5 Ki 5 Ki	B 9 9 8	<u>Status</u>
v VZ v v	001 002 003 004	User01 User02 User03 User04		57 M 5 K 5 K 40 M	B 3 3 8 8 3	<u>Status</u>

The confirmation dialog box appears.

### Note

For more information about the Box Management Subtab, see the following page: P.41 "[Box Management] subtab"

# Click [OK].

Message fr	rom webpage
?	Do you want to delete the item(s)?
	OK Cancel

The selected user boxes are deleted from e-Filing.

### Unlocking user boxes

When the Lockout Setting of e-Filing is set to "Enable" in the Password Policy, if an incorrect user box password is entered a specified number of times consecutively, the user box is locked so that it cannot be used for a certain time. The system administrator can unlock user boxes which have been so locked.

### Note

The Password Policy can be set in TopAccess. For details of the password policy, refer to the TopAccess Guide.

**1** Log on to the Administrator page.

P.37 "Logging in as a system administrator" The Box Management page is displayed.

Tips

- For locked user boxes, "Locked" is displayed in the Status.
- You can display the Box Properties window by clicking the box number or box name link.

### Select the check box of the user box that you want to unlock, and the click [Unlock].

e-Filing Disk Space Available : 101/2 MB Stored Data Box Data Type Data Size Remarks Box Shared File 97 MB		igement						
Box         Shared File         97 M9           Delete         Unlock         Startes           Image: Startes         Box Marre         Used capacity         Startes           Image: Startes         Occ         UserO1         57 MB         Startes           Image: Occ         Occ         UserO1         57 MB         Image: Occ         Image: Oc	e-Filing Disk S							
Deter         Unlock         Box Name         Used capacity         Status           1         21         User01         57 MB         1           002         User02         5 KB         1         0         1							Remarks	
Box Name         Used capacity         Status           21         User01         57 MB           002         User02         548           003         User03         548           004         User04         40 MB           005         User05         548		BUA	onared File	57 MD				
Box Name         Used capacity         Status           1         User01         57 MB           002         User02         5 KB           003         User03         5 KB           004         User04         40 MB         Locked           005         User05         5 KB         5								
Box Name         Used capacity         Status           1         User01         57 MB           002         User02         5 KB           003         User03         5 KB           004         User04         40 MB         Locked           005         User05         5 KB         5								
Box Name         Used capacity         Status           21         User01         57 MB           002         User02         548           003         User03         548           004         User04         40 MB           005         User05         548	Delete Un	lock						
Image: Dot 2         User02         5KB           003         User03         5KB           004         User04         40MB           005         User05         5KB	<u> </u>	Box Number	Box Name		Used ca	apacity	Status	
Image: Constraint of the system         Observation         SMB         SMB           Image: Constraint of the system         004         Uservation         40MB         Locked           Image: Constraint of the system         005         Uservation         5KB         SMB		N201	User01		57	мв		
Image: Constraint of the state of		002	User02		51	<b< td=""><td></td><td></td></b<>		
005 User05 5KB		003	User03		51	<b< td=""><td></td><td></td></b<>		
		004	UserD4		40	MB	Locked	
006 User06 5K8		005	User05		51	<b< td=""><td></td><td></td></b<>		
	en	006	User06		51	<b< td=""><td></td><td></td></b<>		
007 User07 5K8					51	(B		
		006	User06		51	<b< td=""><td></td><td></td></b<>		

The lock of the selected user box is released.

### Note

For more information about the Box Management Subtab, see the following page: P.41 "[Box Management] subtab"

# INDEX

# Α

[Administration] tab	41
Advance automatic delete notification	
All Pages	69
Archive Document	
Authority	81

# В

Binding	66
[Box Management] subtab	
Box Name	41
Box Number	41
Box properties	54

# С

Change Box Password Change Properties Confirm New Password	55 56
Contents Frame	
Copy mode	
Copying	
Copying pages and creating a new document	
Copying the next original	21
Cover/Sheet Insertion	
Insert Pages	67
Interleave Pages	67
Use Back Cover	67
Use Front Cover	67
Creating user boxes	27, 44

# D

Default Document View	40
Delete	
Delete document automatically	
Deleting	
Deleting pages from a document	
Deleting print jobs	14, 16
Deleting scan jobs	21, 24
Department Code	
Destination	66
Destination Setting	82
Display the progress bar	
Displaying folder properties	57
Document	
Delete	
Display	
Merge	
Move	107
Print	64
Rename	61
Send as Email	
Store	70
Document Frame	
Documents	7
Archive	73
[Documents] tab	
Downloading an archived document	73
Duplex	
_	

# Е

Edit mode	88
Editing	
e-Filing Disk Space Available	
e-Filing Features	6
e-Filing Functions	8
Email Address	56

Encryption Encryption Level Erasing boxes	. 81
F [first page number] - [last page number] Pages Folder Create Delete Rename Folders	. 45 . 48 . 52
<b>G</b> Group Copies	. 66
H Hole Punch	. 67
I Image Shift Position In Use Insert Blank Page Inserting a blank page into a document	. 88 102
<b>L</b> Load [number] thumbnails per view	. 40
M Managing user boxes and folders	. 81 . 39 109 107
N	

# Ν

New Box	44
New Folder	46
New Password	56
Number of Copies	66

# 0

Old Password		56
--------------	--	----

### **P** Page

raye	
Copy/Cut	90, 95
Delete	
Move	104
Properties	89
Page Number	
Initial Page	67
Position	67
Paper Source	
Paper Type	
Paper Type (Insert)	
Password	6
Password entry1	
Paste	
[Preferences] tab	
Preservation Period for Documents	
Print Document	
Printing	
Printing a document using Test Print	
5 0	

R	

# 

### S Save a print job In a user box ......71 In the public box .....70 Scanning the next original ......24 Scheduled Print ......67 Send Email when an error occurs ......56 Send Email when job is completed ......56 Shift Margin Status ......41 Storing ......17

### Т

Test Print68	3
Time Stamp	
Position67	7
Tool Bar	9

### U

-	
Unlocking user boxes	115
Upload Archived Document	77
Uploading archived documents	76
Used capacity	41
User box	6
Create	44
Delete	47
Rename	50
User Password	80
V	

View		
------	--	--

ES9455 MFP ES9465 MFP/ES9475 MFP

	•	٠	•	٠	٠	*	٠	٠	*	•	٠	•	٠	٠	٠	*	٠	٠	٠	٠	*	٠	٠	*
	٠	٠	•	•	٠	•	•	•	•	•	٠	•	•	•	•	•	•	•	•	•	•	•	٠	٠
	٠	٠		٠	۰	٠	٠	٠	٠	•	۰	٠	٠	٠	٠	•	٠	٠	•	٠	٠	•	٠	٠
Oki Data Corporation	٠	٠	٠	۰	۰	٠	۰	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠
4-11-22 Shibaura, Minato-ku,Tokyo	•	٠	•	٠	٠	•	•	٠	٠	•	٠	•	٠	٠	٠	•	•	٠	٠	•	•	٠	٠	٠
108-8551, Japan	٠	۰	٠	٠	۰	٠	٠	٠	٠	•	۰	٠	٠	٠	٠	•	٠	۰	٠	٠	٠	٠	٠	٠
	٠	٠	٠	۰	۰	٠	۰	٠	٠	٠	۰	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠
	٠	٠	٠	٠	٠	•	٠	•	٠	•	٠	٠	•	•	٠	*	٠	٠	•	٠	٠	•	•	۰
www.okiprintingsolutions.com	٠	٠	•	٠	٠	*	٠	•	٠	•	٠	٠	•	•	•	•	٠	٠	•	٠	•	•	•	٠
	٠	•	•	٠	•	•	٠	٠	٠	٠	٠	٠	٠	٠	•	٠	٠	٠	٠	٠	•	٠	٠	•
	٠	٠	٠	٠	٠	٠	٠	٠	٠	*	٠	٠	٠	٠	٠	•	٠	٠	٠	٠	٠	٠	٠	٠
	٠	٠	•	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠	٠	•	٠	٠	٠

# 45686031EE